6502 USER NOTES

no. 16 — $2.50

EDITORIAL

6502 FORTH is ready for distribution! I also have seven articles on 6502 FORTH enhancements for future issues. One of the articles even describes how to add machine language monitor-like functions to 6502 FORTH! That really drove home the point to me that FORTH is a complete programming system!

Issues 1-6 of the User Notes have been completely re-typed and are now going in to layout. The typing took longer than we expected so I can't announce back issues as being ready yet. If you would like immediate notification of back issue availability (issues 1-6) please send us a self addressed stamped envelope. As soon as we are ready to take orders, we will let you know the price. Your patience is appreciated.

I don't believe price alone should be the determining factor in purchasing computers software and equipment. This seems to be the case, though, with most of the hobbyists I have spoken with. Consumer education seems to be the way to turn this around.

In an upcoming issue, I plan to present comparison charts for all the 6502 assemblers which are available and another one for the 6502 disk systems.

Hopefully, this will give us all an overall picture of what we're really getting for our bucks.

-Whats Happening-

ROCKWELL has recently added several AIM-65 application notes to their already substantial array of system documentation.

No. R6500 N08 RS-232C INTERFACE FOR AIM-65
R6500 N09 INTERFACING R6500 MICROPROCESSOR TO A FLOPPY DISK CONTROLLER.
R6500 N11 INTERFACING KIM-4 TO AIM-65

R6500 N12 A CRT MONITOR OR TV INTERFACE FOR AIM-65

(The last one is particularly interesting as it presents a complete hardware and software design for a 16 chip 40x16 video interface using the Motorola (and shortly Synertek's) 6845 CRT controller chip. This design looks to be useable on ANY 6502 based system with a 1 MHz clock. Parts costs should be around $100).

These application notes are available at no charge from:

ROCKWELL MICROELECTRONIC DEVICES
MARKETING SERVICES
PO BOX 3669, RC55
ANAHEIM, CA 92803

6502 USER NOTES is published bimonthly by Eric C. Rehnke (POB 33093, N. Royalton, Ohio 44133 (216-237-0755). Subscription rates for Volume 3 are $13.00 (US and Canada) and $19.00 elsewhere. One subscription includes all 6 issues of a volume and cannot carry over part way into the next volume. If less than a full volume is desired, remit $2.50 for each issue wanted.

Rockwell also announced their AIM-65 Expansion Motherboard. This 5-slot backplane is bus compatible with the SYSTEM/65 as well as the Motorola Exorciser. Its priced at $195. For a complete product description which includes a complete schematic, ask for document number 29650 N57.

SYNERTEK has dropped the retail price of the SYM to $239!

They've also introduced several new chips which should help to bolster the 65XX family image. One of these chips, the 6551 ACIA, is mentioned in the 65XX FAMILY CHIP STUFF section elsewhere in this newsletter. The other new chips, the 6545 CRT controller and the floppy disc controller are not into production yet and will be mentioned more when they are real.

HDE has been shipping their mini-floppy systems and their cassette based assembler/editor package.

A number of firms, including HDE, have been caught in the industry wide LS (low power Schotky) component shortage which has been playing OEM's for most of the summer.

Before ordering anything that might contain LS components, it might be worth a phone call or a letter to the supplier to see what the situation is. This shouldn't be regarded as a blanket excuse for slow delivery times from suppliers but could be a possible explanation.

An outfit called Perry Peripherals is adapting the HDE mini floppy system to the S-100/KIMSI system. Should have more info by next issue.

We now have a European distributor! European stores can contact:

ING. W. HOFACKER GMBH
8 MUNCHEN 75
POSTFACH 437
WEST GERMANY

An aquaintance of mine and a fellow ex-MOS Technology employee, Ray Bennett, President of RNB Enterprises, called me the other day with some disturbing news. Ray indicated that he noticed a very substantial decrease in his mail order business when the news of the World Power Systems fraud became known.

It's the old story of a few unsavory types messing things up for the rest.

LOCAL 6502 ORIENTED USER GROUPS

LICA (Long Island Computer Assoc.)
#6 Brookhaven Dr.
Rocky Point, NY 11778

SAN FERNANDO VALLEY 6502 USERS CLUB meet at 8:00 PM on the 2nd Tuesday of each month at Computer Components of Burbank, 3808 West Verdugo Ave, Burbank CA 91505. Contact Larry Goga (3816 Albright Ave, Los Angeles, CA 90066, 213-398-6086), for more info. This group also publishes a monthly newsletter which is available for $2.00 a year. Useful stuff!

WAKE--Washington Area KIM Enthusiasts--meet each month at the McGraw-Hill Continuing Education Center in Washington, D.C. to study operation, expansion, and applications of KIM 1 microcomputers. Meetings are at 7:30 on the third Wednesday of every month.

For a copy of the current WAKE newsletter, send a stamped, self-addressed envelope to WAKE, c/o Ted Beach, 5112 Williamsburg Blvd., Arlington, VA 22207, or phone (703) 538-2303.

FOUR PART HARMONY (cheap!!)

KIM-1 MUSIC PROGRAM

by Richard Martin

(A) ABSTRACT

The KIM-1 music program "plays" music in four part harmony on an unexpanded KIM-1 micro-computer.

(B) EQUIPMENT REQUIRED:

KIM-1 module with power supply, four (4) 150K ohm resistors, a 2.2 uF capacitor, an audio amplifier, and speaker. Refer to Figure 1 for hardware connection.

(C) OPERATION

The program causes a series of 75 microsecond pulses to be output on each of four PIA terminals (PA0-PA3). The frequency of the pulse waveform on each terminal is independently controlable by data stored in the KIM-1 memory. The pulses are mixed together by a simple resistance network and coupled through a capacitor to an ordinary audio amplifier.

(D) USAGE

The program accepts three different types of coded notes: normal, compressed, and branch.



FIGURE 1.

(1) Normal notes:

These notes require two bytes of storage.



Frequency code-Determines pitch of note. Refer to Figure 2 for a list of pitches and their respective codes. Notice that a frequency code of 00 (hex) specifies a rest (no tone generated).

Duration code-Determines length of note. The note will be held for the number of counts specified by the duration code. The codes in Figure 3 are recommended for most work.

Examples: 33 08 causes middle C to be played for eight counts. (eighth note)
2E 20 causes A above middle C to be played for 32 counts. (half note)

After the note is over, the playing program goes to the next consecutive byte in storage to fetch the next note.

	79	(-1.19)
		72 (+1.97)
	6C	(-4.42)
	66	(-5.47)
		60 (-0.51)
	5B	(-7.91)
		56 (-10.07)
	51	(-6.38)
	4C	(+3.92)
		48 (-2.47)
	44	(-3.51)
		40 (+1.43)
	3C	(+13.17)
		39 (+1.97)
	36	(-4.42)
MIDDLE C	33	(-5.47)
		30 (-0.51)
	2D	(+11.21)
		28 (-10.07)
	28	(+15.12)
	26	(+3.92)
		24 (-2.47)
	22	(-3.51)
		20 (+1.43)
	1E	(+13.16)

Frequency codes are in hexadecimal. Numbers in () are the relative tuning in cents. This is to provide some idea of how out-of-tune the notes are (a pitch difference of 6 cents can be detected only by very sensitive ears).

figure 2.

(2) Compressed notes:

If several notes with the same duration are to be played in succession, they can be shortened to one byte each, conserving considerable amounts of memory space.

The pitch will change to that specified by the new frequency code. The duration code, however, will remain the same as it was for the last note.



Example:

This is how the C scale would be coded:

```
66 20
58 10
D1
CC
C4
BC
B6
33 40
```

(3) Branch notes:

Branch notes are similar to normal notes, however, instead of going to the next consecutive address in memory for the next notes, the branch note causes the program to jump to a new address for the next note. Branch notes require four bytes in storage.



When the branch note is over, the next note played will be the one with its 1st byte at the new address. Branch notes are useful for making a song repeat, and for skipping unusable addresses in memory.



Figure 3

(E) PROGRAMMING TECHNIQUES

(1) Locations 0000-00CB and 0100-010F are used by the playing program. All other locations may be used for music data. Music data normally resides from 0110-03FF.

(2) The stack pointer should always be set to 0A before loading music data. Otherwise, the stack may overwrite the music data.

(3) Keep in mind that the playing program is capable of playing four independent melodies simultaneously. The melodies or "parts" should be placed one after another in memory.

(4) Once all four parts have been loaded, the playing program's internal pointers and counters must be initialized as followw:

```
ADDR
0008  LSB
          Starting address-1 for the first part
0009  MSB

000A  LSB
          Starting address-1 for the second
          part
000B  MSB

000C  LSB
          Starting address-1 for the third
          part
000D  MSB

000E  LSB
          Starting address-1 for the fourth
          part
000F  MSB
```

Locations 0010-0017 must be set to 01. The tempo is set at location 0007. Tempos range from 10-FF with FF being the slowest.

The playing program can now be started at location 0000.

(5) The playing program "slurs" the notes together (no seperation between the notes). Therefore:

```
cannot be coded as : 44  10  or  44  10
                     44  10      C4
```

To make the notes sound seperate, remove one count from the first note and insert one count of rest between the two notes. The example above would then be coded as:

```
44  0F
00  01
44  10
```

Similar techniques may be employed to give staccato notes.

(6) An optional patch may be inserted into the program to make the fourth part sound an octave lower:

(refer to program listing)

Change loc. 009C from 40 to CC. Then Add:

```
00CC    A6 16       LDX  DURD
00CE    E4 17       CPX  XDURD
00D0    D0 04       BNE  Q
00D2    06 26       ASL  PD
00D4    06 27       ASL  XD
00D6    4C 40 00 Q  JMP  TONE
```

The patch occupies locations 00CC-00D8. Similar routines may be written for the other parts if necessary.

```
HDE ASSEMBLER REV 2.0

LINE#  ADDR   OBJECT     SOURCE          PAGE 0001

 0010  2000              ;KIM-1 MUSIC PROGRAM
 0020  2000              ;WRITTEN BY RICHARD MARTIN 5/76
 0030  2000              ;
 0040  2000              ;I/O AND TIMER ADDRESSES
 0050  2000              PIA     =$1700          ;OUTPUT REGISTER
 0060  2000              DDR     =$1701          ;DATA DIRECTION REGISTER
 0070  2000              TIMER   =$1707          ;INTERVAL TIMER
 0080  2000              ;
 0090  2000              ;INITIALIZE PIA AND START
 0100  2000                      *=$0
 0110  0000                      .OFF 2000
 0120  0000  A9 0F       START   LDA #$F
 0130  0002  8D 01 17            STA DDR
 0140  0005  D0 69               BNE NEW
 0150  0007              ;
 0160  0007              ;Z PAGE VARIABLES AND CONSTANTS
 0170  0007              ;
 0180  0007              TEMPO   *=*+1
 0190  0008              PTAL    *=*+1           ;CURRENT NOTE POINTERS
 0200  0009              PTAH    *=*+1
 0210  000A              PTBL    *=*+1
 0220  000B              PTBH    *=*+1
 0230  000C              PTCL    *=*+1
 0240  000D              PTCH    *=*+1
 0250  000E              PTDL    *=*+1
 0260  000F              PTDH    *=*+1
 0270  0010              DURA    *=*+1           ;NOTE DURATION COUNTERS
 0280  0011              XDURA   *=*+1           ;CURRENT NOTE DURATION
 0290  0012              DURB    *=*+1
 0300  0013              XDURB   *=*+1
 0310  0014              DURC    *=*+1
 0320  0015              XDURC   *=*+1
 0330  0016              DURD    *=*+1
 0340  0017              XDURD   *=*+1
 0350  0018              RSTA    *=*+1           ;USED FOR OUTPUT SWITCHING
 0360  0019  01          X01     .BYTE $1
 0370  001A              RSTB    *=*+1
 0380  001B  02          X02     .BYTE $2
 0390  001C              RSTC    *=*+1
 0400  001D  04          X04     .BYTE $4
 0410  001E              RSTD    *=*+1
 0420  001F  08          X08     .BYTE $8
 0430  0020              PA      *=*+1           ;PITCH COUNTERS
 0440  0021              XA      *=*+1           ;CURRENT PITCH
 0450  0022              PB      *=*+1
 0460  0023              XB      *=*+1
 0470  0024              PC      *=*+1
 0480  0025              XC      *=*+1
 0490  0026              PD      *=*+1
 0500  0027              XD      *=*+1
 0510  0028  FE          R01     .BYTE $FE       ;USED FOR OUTPUT SWITCHING
 0520  0029  FD          R02     .BYTE $FD
 0530  002A  FB          R04     .BYTE $FB
 0540  002B  F7          R08     .BYTE $F7
 0550  002C              ;
 0560  002C              ;RESET AND DELAY ROUTINES
 0570  002C              ;FOR TONE GENERATION
 0580  002C              ;
 0590  002C  25 28       DELA    AND R01         ;TURN OFF OUTPUT A
 0600  002E  EA                  NOP             ;WASTE MORE TIME
 0610  002F  D0 19               BNE RA          ;JUMP BACK TO MAIN ROUTINE
 0620  0031  25 29       DELB    AND R02
 0630  0033  EA                  NOP
 0640  0034  D0 1E               BNE RB
 0650  0036  25 2A       DELC    AND R04
 0660  0038  EA                  NOP
 0670  0039  D0 23               BNE RC
 0680  003B  25 2B       DELD    AND R08
 0690  003D  EA                  NOP
 0700  003E  D0 28               BNE RD
 0710  0040              ;
 0720  0040              ;MAIN TONE GENERATION ROUTINE
 0730  0040              ;
 0740  0040  C6 20       TONE    DEC PA          ;DECREMENT PITCH CNTR 'A'
 0750  0042  D0 E8               BNE DELA
 0760  0044  A6 21               LDX XA          ;RESTORE PITCH COUNTER
 0770  0046  86 20               STX PA
 0780  0048  05 18               ORA RSTA
 0790  004A  C6 22       RA      DEC PB
 0800  004C  D0 E3               BNE DELB
 0810  004E  A6 23               LDX XB
 0820  0050  86 22               STX PB
 0830  0052  05 1A               ORA RSTB
 0840  0054  C6 24       RB      DEC PC
 0850  0056  D0 DE               BNE DELC
```

```
0860  0058  A6 25           LDX XC
0870  005A  86 24           STX PC
0880  005C  05 1C           ORA RSTC
0890  005E  C6 26     RC    DEC PD
0900  0060  D0 D9           BNE DELD
0910  0062  A6 27           LDX XD
0920  0064  86 26           STX PD
0930  0066  05 1E           ORA RSTD
0940  0068  8D 00 17  RD     STA PIA         ;UPDATE ALL OUTPUTS
0950  006B  2C 07 17        BIT TIMER       ;HAS AN INTERVAL PASSED?
0960  006E  10 D0           BPL TONE        ;NO, KEEP GENERATING TONES
0970  0070                 ;
0980  0070                 ;THIS ROUTINE UPDATES THE NOTES
0990  0070                 ;
1000  0070  A2 00     NEW   LDX #$0         ;INITIALIZE X-INDEX REG
1010  0072  D6 10     NEW1  DEC DURA,X      ;DECREMENT DURATION CNTR
1020  0074  D0 18           BNE NXT         ;GO ON TO NEXT
1030  0076  20 C3 00        JSR INPTLA      ;GET NEXT PITCH
1040  0079  30 23           BMI SMDUR       ;IF MSB=1, USE SAME DURATION
1050  007B  95 21           STA XA,X        ;STORE THE PITCH
1060  007D  95 20           STA PA,X
1070  007F  F0 02           BEQ NEW2        ;IF REST, STORE 00 IN RSTA
1080  0081  B5 19           LDA X01,X       ;OTHERWISE, USE X01
1090  0083  95 18     NEW2  STA RSTA,X
1100  0085  20 C3 00        JSR INPTLA      ;GET NEXT DURATION
1110  0088  30 25           BMI BRNCH       ;IF MSB=1, NOTE IS A BRANCH
1120  008A  95 11           STA XDURA,X     ;STORE THE DURATION
1130  008C  95 10     NEW3  STA DURA,X
1140  008E  E8       NXT   INX             ;SET 'X' TO UPDATE NEXT NOTE
1150  008F  E8              INX
1160  0090  E0 08           CPX #$8         ;IF 'X'=8, THEN...
1170  0092  D0 DE           BNE NEW1        ;WE ARE DONE
1180  0094  A5 07           LDA TEMPO       ;INITIALIZE THE TIMER
1190  0096  8D 07 17        STA TIMER
1200  0099  A9 10           LDA #$10        ;INITIALIZE THE ACCUMULATOR
1210  009B  4C 40 00        JMP TONE        ;RESUME TONE GENERATION
1220  009E                 ;
1230  009E                 ;ROUTINE FOR COMPRESSED NOTES
1240  009E                 ;
1250  009E  29 7F     SMDUR AND #$7F        ;SET MSB =0
1260  00A0  95 21           STA XA,X        ;STORE THE PITCH
1270  00A2  95 20           STA PA,X
1280  00A4  F0 02           BEQ SMDU2       ;IF REST, STORE 0 IN RSTA
1290  00A6  B5 19           LDA X01,X       ;OTHERWISE, USE X01
1300  00A8  95 18     SMDU2 STA RSTA,X
1310  00AA  B5 11           LDA XDURA,X     ;USE THE DURATION FROM
1320  00AC  4C 8C 00        JMP NEW3        ;THE LAST NOTE
1330  00AF                 ;
1340  00AF                 ;BRANCH ROUTINE
1350  00AF                 ;
1360  00AF  29 7F     BRNCH AND #$7F        ;SET MSB =0
1370  00B1  95 11           STA XDURA,X     ;STORE THE DURATION
1380  00B3  95 10           STA DURA,X
1390  00B5  20 C3 00        JSR INPTLA      ;GET LSB OF BRANCH ADDRESS
1400  00B8  A8              TAY             ;MOVE IT TO 'Y' TEMPORARILY
1410  00B9  20 C3 00        JSR INPTLA      ;GET MSB OF BRANCH ADDRESS
1420  00BC  95 09           STA PTAH,X      ;STORE IT IN HI ORDER PNTR
1430  00BE  94 08           STY PTAL,X      ;STORE LSB OF BRANCH ADDRESS
1440  00C0  4C 8E 00        JMP NXT
1450  00C3                 ;
1460  00C3                 ;SUBROUTINE TO INCREMENT POINTER
1470  00C3                 ;AND LOAD ACCUMULATOR FROM THE ADDRESS
1480  00C3                 ;HELD BY THE POINTER
1490  00C3                 ;
1500  00C3  F6 08     INPTLA INC PTAL,X     ;INC LOW ORDER BYTE OF PNTR
1510  00C5  D0 02           BNE INPT2       ;IF THERE IS A CARRY
1520  00C7  F6 09           INC PTAH,X      ;THEN INC HI ORDER BYTE
1530  00C9  A1 08     INPT2 LDA (PTAL,X)    ;LOAD ACC FROM INDIRECT
1540  00CB  60              RTS             ;POINTER AND RETURN
1550  00CC                 ;
1560  00CC                 ;
1570  00CC                 FINISH .END
```

DEMO TUNE TABLE

This song table occupies locations $0110-$0318. Before loading this song table in by hand or by cassette, BE SURE TO set the stack pointer to $0A by entering $0A into location $00F2 (SP). This is important!!! Remember that RESET will reset the stack to $FF. By the way, the name of the song is "Here's That Rainy Day" by Van Heusen.

Oh yes, so that the music program knows where the music table is, you must fill in the following data in the music program's pointer locations:

$0008 0F 01
$000A CF 01
$000C 4F 02
$000E CF 02

```
110  48 07 00 01 48 0F 00 01 48 07 00 01 48 08 BC AD
120  24 07 00 01 24 10 28 08 AB 28 20 48 07 00 01 48
130  0F 00 01 48 07 00 01 48 08 B9 B0 A8 2B 38 00 08
140  22 0F 00 01 22 0F 00 01 22 08 B6 B3 B0 24 10 3C
150  08 B9 36 10 39 08 B6 28 07 00 01 28 0F 00 01 28
160  07 00 01 28 08 C0 BC B9 2B 40 48 07 00 01 48 0F
170  00 01 48 07 00 01 48 08 BC AD 24 07 00 01 24 10
180  28 08 AB 28 20 48 07 00 01 48 0F 00 01 48 07 00
190  01 48 08 B9 B0 A8 2B 38 00 08 20 07 00 01 20 0F
1A0  00 01 20 07 00 01 20 08 B0 AB A8 24 10 39 08 B6
1B0  30 20 48 07 00 01 48 0F 00 01 48 07 00 01 48 08
1C0  B9 B0 AB 36 28 00 98 0F 01 40 40 40 C0 C0 40 00
1D0  56 20 5B 10 36 30 39 20 51 30 44 10 30 10 36 08
1E0  B9 40 10 C8 36 17 00 01 36 08 44 20 48 30 4C 10
1F0  51 37 00 01 51 08 30 07 00 01 30 0F 00 01 30 07
```

```
200  00 01 36 07 00 01 36 0F 00 01 36 08 56 20 5B 10
210  36 30 39 20 51 30 44 10 39 07 00 01 39 0F 00 01
220  40 07 00 01 44 07 00 01 44 0F 00 01 44 07 00 01
230  36 20 39 20 48 10 44 08 C8 4C 20 51 40 40 10 2B
240  08 A4 AB B6 C0 44 88 CF 01 3F 3D 3F BF 7E 3C B9
250  36 10 B9 C8 D1 DB AD AD B0 B6 C0 B9 51 08 F9 80
260  C8 C0 B9 B6 B0 A8 AB 2D 17 00 01 2D 08 30 10 B9
270  3C 08 B0 B6 B9 3C 10 C0 C0 BC 39 08 B6 B3 B0 39
280  07 00 01 39 0F 00 01 39 07 00 01 40 07 00 01 40
290  0F 00 01 40 08 36 10 B9 BC C0 DB AD AD B0 B6 C0
2A0  B9 51 08 F9 48 07 00 01 48 0F 00 01 40 08 BC B6
2B0  B3 B0 2B 10 AD 30 28 36 08 B9 C0 36 20 E0 48 10
2C0  40 08 C4 C8 C8 A4 AB B6 C0 39 90 4F 02 A9 3C 3D
2D0  00 30 24 10 00 40 80 80 80 80 00 38 51 08 48 07
2E0  00 01 48 0F 00 01 48 07 00 01 48 07 00 01 48 0F
2F0  00 01 48 08 00 30 48 10 00 40 80 56 07 00 01 56
300  0F 00 01 56 07 00 01 56 07 00 01 56 0F 00 01 56
310  08 00 40 80 80 00 C0 CF 02
```

CIRCULAR LIST PROCESSING SUBROUTINES

Jim Adams
17272 Dorset
Southfield, MI 48075

Did you ever wish you had a stack for data storage which wasn't messed up by interrupts and subroutine calls? How about a stack where you could easily get at the first thing put on instead of the last? These circular list (or stack) processing subroutines perform the pointer, data and counter manipulations to reduce the above functions to subroutine calls.

A circular list is a block of memory which wraps around at the ends (figure 1). The last slot and the first slot are next to each other. The subroutines use four pieces of information about each list. The number of available slots tells when to wrap around and when the list is full or empty. The current top and next bottom point to the data. This information is kept with each list in the order shown in figure 2.

To initialize a block of memory to be used as a list put the address of the list in $EC (low, high) and the number of slots (n) you want in $EA, then JSR INL. Use JSR INLO when n is in register A instead of in $EA. The number of slots will be set to n and the other three parameters will be set to 0.

To add data to the list, put the address of the list in $EB, $EC and the data in $EA, then JSR ATL or JSR ABL. Or you can put the data in register A and JSR ATLO or JSR ABLO. If the list is full the V bit will be set, the list will remain unchanged and $EA will contain the data. If the list is not full the V bit will be clear, $EA and register A will contain the data, N and Z will reflect the value of the data, and the data will be added to the list.

To remove data from the list, put the address of the list in $EB, $EC then JSR RBL or JSR RTL. If the list is empty the V bit will be set. If the list is not empty V will be clear, $EA and register A will contain the data, N and Z will reflect the value of the data and the data will be removed from the list.

This version restricts the list and its parameters to a page so the maximum number of slots in any list is $FC. If you ask for more slots the parameters will be overwritten with data. If you ask for more slots than remain to the end of a page then the extra slots are at the beginning of the same page, not the next page. The V bit is set with BIT $1A09. This is a location in the KIM monitor containing a $40. To use the subroutines with SYM or AIM change $1A09 to any location where bit 6 is set (e.g., to an RTS location). Location $FC is used for temporary storage.

Circular lists can be used as first-in first-out buffers for asynchronous data transmission, queue storage, breadth-first search storage, failure sequence analysis, order preserving sorts, fixed sequence delays among other things. They can also be used like the 650X stack as first-in last-out buffers for depth-first search storage and reentrant subroutine storage.

```
0020  2000                ;ZERO PAGE REGISTERS TO FOLLOW
0025  2000                      *=$0
0030  0000                DATA  *=*+1             ;THIS LOCATION HOLDS THE NUMBER
0035  0001                ;OF SLOTS FOR SUBROUTINE 'INL' OR DATA TO
0040  0001                ;BE TRANSFERED TO LIST FOR 'ABL' OR 'ATL'
0045  0001                ;OR DATA TAKEN FROM LIST BY 'RBL' OR 'RTL'.
0050  0001
0055  0001                LPTR  *=*+2             ;ADDRESS LOW, HIGH OF LIST
0060  0003
0064  0003                TEMP  =$00FC            ;TEMPORARY SAVE LOCATION
0065  0003                ;THE LIST SETUP IN MEMORY IS:
0070  0003
0075  0003                ;     LIST   SLOTS AVAILABLE    1ST BYTE
0080  0003                ;            NUMBER USED        2ND BYTE
0085  0003                ;            CURRENT TOP        3RD BYTE
0090  0003                ;            NEXT BOTTOM        4TH BYTE
0095  0003                ;            1ST SLOT           5TH BYTE
0100  0003                ;               .                  .
0105  0003                ;               .                  .
0110  0003                ;            LAST SLOT          $AVAIL/4TH BYTE
0115  0003                ;
0120  0003                ;USE OF (IND),Y ADDRESSING AND FOUR BYTE OVERHEAD
0125  0003                ;MEANS MAX NUMBER OF SLOTS PER LIST IS $FC.
0130  0003
0135  0003                ;ENTRY POINTS;
0140  0003                ;     INLO    INITIALIZE LIST, # SLOTS IN 'A'
0145  0003                ;     INL     INITIALIZE LIST, # SLOTS IN 'DATA'
0150  0003                ;     ATLO    CONTENTS OF 'A' TO TOP OF LIST
0155  0003                ;     ATL     CONTENTS OF 'DATA' TO TOP OF LIST
0160  0003                ;     ABLO    CONTENTS OF 'A' TO BOTTOM OF LIST
0165  0003                ;     ABL     CONTENTS OF 'DATA' TO BOTTOM OF LIST
0170  0003                ;     RBL     CONTENTS OF BOTTOM OF LIST TO 'A' AND 'DATA'
0175  0003                ;     RTL     CONTENTS OF TOP OF LIST TO 'A' AND 'DATA'
0180  0003
0185  0003                ;STATUS:  V BIT IS SET IF ATTEMPT IS MADE TO ADD TO A
0190  0003                ;              FULL LIST OR REMOVE FROM AN EMPTY ONE.
0195  0003                ;         V BIT IS CLEAR IF SUCESSFUL TRANSFER  OCCURS.
0200  0003
0205  0003                      *=$2000
0210  2000
0215  2000  85 00         INLO  STA DATA          ;INITIALIZE LIST
0220  2002  A0 00         INL   LDY #0            ;C(DATA) TO
0225  2004  A5 00               LDA DATA          ;NUMBER OF SLOTS USED
0230  2006  91 01               STA (LPTR),Y
0235  2008  A9 00               LDA #0            ;ZERO TO...
0240  200A  C8                  INY
0245  200B  91 01               STA (LPTR),Y      ;...NUMBER USED
0250  200D  C8                  INY
0255  200E  91 01               STA (LPTR),Y      ;...CURRENT TOP
0260  2010  C8                  INY
```

```
0265  2011  91 01           STA (LPTR),Y    ;...NEXT BOTTOM
0270  2013
0275  2013  85 00     ATLO  STA DATA        ;ADD TO TOP OF LIST
0280  2015  20 77 20  ATL   JSR FULL        ;SLOTS AVAILABLE?
0285  2018  70 4E           BVS END2        ;...EXIT IF NOT
0290  201A  20 BB 20        JSR POINT       ;YES, POINT TO
0295  201D  A5 00     PUT   LDA DATA        ;SLOT AND STUFF
0300  201F  4C 63 20        JMP END1        ;DATA
0305  2022
0310  2022  20 69 20  RBL   JSR EMPTY       ;REMOVE FROM BOTTOM
0315  2025  70 41           BVS END2        ;EXIT IF EMPTY
0320  2027  C8              INY
0325  2028  20 BB 20        JSR POINT       ;POINT TO SLOT
0330  202B  B1 01     GET   LDA (LPTR),Y    ;AND GET CONTENTS
0335  202D  85 00           STA DATA        ;TO 'DATA'
0340  202F  4C 65 20        JMP END3
0345  2032
0350  2032  20 69 20  RTL   JSR EMPTY       ;REMOVE FROM TOP
0355  2035  70 31           BVS END2        ;EXIT IF EMPTY
0360  2037  20 A1 20        JSR POINT1      ;POINT TO SLOT
0365  203A  20 2B 20        JSR GET         ;AND GET CONTENTS
0370  203D  A0 02           LDY #2          ;UPDATE CURRENT TOP
0375  203F  D0 10           BNE END         ;(UNCONDITIONAL)
0380  2041
0385  2041  85 00     ABLO  STA DATA        ;ADD TO BOTTOM
0390  2043  20 77 20  ABL   JSR FULL        ;SLOT AVAILABLE?
0395  2046  70 20           BVS END2        ;EXIT IF NOT
0400  2048  C8              INY             ;YES,
0405  2049  20 A1 20        JSR POINT1      ;POINT TO SLOT
0410  204C  20 1D 20        JSR PUT         ;AND STUFF DATA
0415  204F  A0 03           LDY #3          ;THERE
0420  2051
0425  2051  84 FC     END   STY TEMP
0430  2053  A0 00           LDY #0          ;NUMBER OF SLOTS SAME
0435  2055  B1 01           LDA (LPTR),Y    ;AS POINTER PLUS 1?
0440  2057  A4 FC           LDY TEMP
0445  2059  18              CLC
0450  205A  F1 01           SBC (LPTR),Y    ;IF SO,
0455  205C  F0 05           BEQ END1        ;RESET POINTER
0460  205E  B1 01           LDA (LPTR),Y    ;OTHERWISE
0465  2060  38              SEC             ;DECREMENT POINTER
0470  2061  69 00           ADC #0
0475  2063  85 01     END1  STA LPTR
0480  2065  A5 00     END3  LDA DATA
0485  2067  B8              CLV
0490  2068  60        END2  RTS
0495  2069
0500  2069                 ;SUBROUTINES TO CHECK LIST FULL OR EMPTY.
0505  2069                 ;V FLAG IS SET WHEN ANSWER IS "YES".
0510  2069                 ;IF ANSWER IS NO, SUBROUTINES INCREMENT
0515  2069                 ;OR DECREMENT NUMBER OF SLOTS USED IN
0520  2069                 ;ANTICIPATION OF A 'PUT' OR 'GET'.
0525  2069                 ;AT RTS, 'Y' POINTS TO CURRENT TOP POINTER.
0535  2069  A0 01     EMPTY LDY #1          ;GET NUMBER OF
0540  206B  B1 01           LDA (LPTR),Y    ;SLOTS USED
0545  206D  F0 11           BEQ EMPTY1      ;BRANCH IS NONE
0550  206F  18              CLC             ;DECREMENT
0555  2070  E9 00           SBC #0          ;NUMBER USED
0560  2072  91 01     OUT   STA (LPTR),Y
0565  2074  C8              INY             ;TO CURRENT TOP POINTER
0570  2075  B8              CLV
0575  2076  60              RTS
0580  2077
0585  2077  A0 00     FULL  LDY #0          ;SLOTS AVAILABLE
0590  2079  B1 01           LDA (LPTR),Y    ;SAME AS
0595  207B  C8              INY             ;SLOTS USED?
0600  207C  51 01           EOR (LPTR),Y
0605  207E  D0 04           BNE INCR        ;BRANCH IF NOT
0610  2080  2C 09 1A  EMPTY1 BIT $1A09       ;SET V FLAG
0615  2083  60              RTS
0620  2084  A9 00     INCR  LDA #0          ;INCREMENT
0625  2086  38              SEC             ;NUMBER USED
0630  2087  71 01           ADC (LPTR),Y
0635  2089  D0 E7           BNE OUT         ;(UNCONDITIONAL)
0640  208B
0645  208B                 ;SUBROUTINES TO POINT TO LIST DATA
0650  208B
0655  208B  B1 01     POINT LDA (LPTR),Y    ;POINTS TO SLOT 1
0660  208D  D0 0D           BNE NOSET       ;BRANCH IF NOT
0665  208F  84 FC           STY TEMP        ;YES, SAVE INDEX,
0670  2091  A0 00           LDY #0          ;GET NUMBER OF
0675  2093  B1 01           LDA (LPTR),Y    ;SLOTS MINUS 1
0680  2095  18              CLC             ;(LAST SLOT)
0685  2096  E9 00           SBC #0          ;THIS 'DECREMENTS'
0690  2098  A4 FC           LDY TEMP        ;THE POINTER
0695  209A  D0 03           BNE OVER
0700  209C  18        NOSET CLC             ;DECREMENT
0705  209D  E9 00           SBC #0          ;POINTER
0710  209F  91 01     OVER  STA (LPTR),Y
0715  20A1  B1 01     POINT1 LDA (LPTR),Y   ;GET POINTER
0720  20A3  18              CLC             ;AND ADD
0725  20A4  69 04           ADC #4          ;OFFSET TO
0730  20A6  A8              TAY             ;FIRST SLOT
0735  20A7  60              RTS
```

HDE inc.

BOX 120
ALLAMUCHY, N.J. 07820
201-362-6574

HUDSON DIGITAL ELECTRONICS INC.

THE HDE DISK SYSTEM.

HERE'S WHAT ONE USER HAS TO SAY . . .

REPRINTED BY PERMISSION FROM THE 6502 USER NOTES - ISSUE NO. 14

PRODUCT REVIEW of the HDE DISC SYSTEM by the editor.

A number of you have asked for details about the HDE full size disc system.

The system is based around the SYKES 8" drive with the 6502 based intelligent controller.

This drive is soft sectored, IBM compatible, and single density which lets you store about a quarter megabyte of data on a disc.

The system software, called FODS (File Oriented Disc System), manages sequential files on the disc much the same way files are written on magnetic tape – one after another. When a file is deleted, from a sequentially managed file system, the space that the file occupied is not immediately reallocated, as in some disc operating systems. As it turns out, this can be an advantage as well as a disadvantage since deleted files on the FODS system can be recovered after the file has been deleted. (This has saved my sanity more than once!) Of course when you want to recover some of the disc space taken up by a number of these deleted files, you can simply re-pack or compress the disc and all the active files will be shifted down until there are no deleted files hanging around using up space.

FODS has this ability to repack a disc.

When saving and loading in FODS you work with named files, not track and sector data or I.D. bytes. This makes life a lot easier. I've seen some disc systems where you have to specify track and sector info and/or I.D. bytes. What a pain that can be!

If you just want to save a source file temporarily, you can do that on what's known as "scratch-pads". There are two of these on a disc, "scratch-pad A" and "scratch-pad B", each of these temporary disc files can hold up to 16K or if "B" is not used, "A" can hold one file up to 32K in length. The only files that can be temporarily saved on scratch pad are files that have been built using the system text editor.

Being a dyed in the wool assembly language programmer, I really appreciate the FODS text editor! This line oriented editor is upwards compatible with the MOS/ARESCO editor but includes about everything you could ask for in a line editor. There is a full and semi-automatic line numbering feature, lines can be edited while they are being entered or recalled and edited later, strings can be located and substituted, the line numbers can be resequenced, the file size can be found, the hex address of a line can be known and comments can be appended to an assembly file after it has been found correct. Oops! forgot to say lines can also be moved around and deleted. This isn't the complete list of FODS editor commands, just the ones that immediately come to mind.

Another very powerful feature of the system is the ability to actually execute a file containing a string of commands. For example, the newsletter mailing list is now being stored on disc. When I want to make labels, I would normally have to load each letter file and run the labels printing program. But with FODS, I can build up a "JOB" file of commands and execute it.

The job file in turn calls each lettered label file in and runs the label printer automatically. The way computers are supposed to operate right?

Here's a listing of the job file I use to print mailing labels:

```
:LIS PRTLBL
0005 LOD A:RUN %LABEL:LOD B:JMP.E000:
LOD C:JMP.E000:
0010 LOD D:JMP.E000:LOD E:JMP.E000:
LOD F:JMP.E000:
0015 LOD G:JMP.E000:LOD H:JMP.E000:
LOD I:JMP.E000:
0020 LOD J:JMP.E000:LOD K:JMP .E000:
LOD L:JMP.E000:
0025 LOD M:JMP.E000:LOD MC: JMP.E000:
LOD N:JMP.E000:
0030 LOD O:JMP.E000:LOD P:JMP .E000:
LOD R:JMP.E000:
0035 LOD S:JMP.E000:LOD T:JMP .E000:
LOD V:JMP.E000:
0035 LOD S:JMP.E000:LOD T:JMP .E000:
LOD V:JMP.E000:
0040 LOD W:JMP.E000:LOD XYZ: JMP.E000:
0045 LOD EXCH:JMP.E000:LOD COMP:
JMP.E000:
```

Remember the MOS/ARESCO assembler I reviewed several issues ago? Well HDE went and fixed up all the problem areas that I mentioned in the review and then took it several steps further. The HDE assembler is an honest to goodness two-pass assembler which can assemble anywhere in memory using multiple source files from the disc. The assembler is an optional part of the system.

If you're the kind of person (as I am) who enjoys having the ability to customize, modify, and expand everything you own – you'll enjoy the system expansion abilities FODS has to offer. Adding a new command is as simple as writing the program, giving it a unique three letter name and saving it to disc. Whenever you type those three letters the system will first go through its own command table, see that its not there and then go out and read the disc directory to see if it can find it. If it's on the disc it will read it in and execute it. Simple right? I've added several commands to my system and REALLY appreciate having this ability. Some of the things I've added include a disassembler, an expanded version of XIM (the extended machine language monitor from Pyramid Data), Hypertape, and a number of system utilities which make life easier. By the way, to get back to the system, all you need to do is execute a BRK instruction.

HDE also provides a piece of software that lets you interface Microsoft 9 digit BASIC to their disc system. The software allows you to load the BASIC interpreter itself from disc as well as saving and loading BASIC Programs to and from the disc. This particular version of the software doesn't allow for saving BASIC data but HDE mentioned that this ability may be possible with a future version.

The first thing I do with a new piece of software after I get used to using it is try to blow it up. I did manage to find a weak spot or two in the very first version of FODS (a pre-release version) but the later, release version has been very tight.

The standard software that is included with the system consists of the disc driver software, the system text editor and the BASIC software interface. Several command extensions may also be included. All the necessary stuff like a power supply, the KIM-4 interface card, and all cables and connectors are included. It took me about 45 minutes to get things up and running the first time I put the system together.

Admittedly, a dual full size disc system from HDE is probably beyond the means of most hobbyists but if you or your company is looking for a dynamite 6502 development system, I would recommend this one. I've used the Rockwell System 65 while I was at MOS and feel that dollar for dollar, feature for feature, the HDE system comes out on top. The only place the HDE system falls short when stacked up next to the System 65 is in the area of packaging. At this point, there is no cabinet for the disc drives available from HDE.

So far, I've got nothing but good things to say about HDE and their products. Everything I've received from them has been industrial quality. That includes their documentation and product support. I'm very impressed with what I've seen from this company so far and quite enthusiastic over what my KIM has become since acquiring the disc system and its associated software.

ERIC

THANK YOU MR. REHNKE!

HDE PRODUCTS – BUILT TO BE USED WITH CONFIDENCE
AVAILABLE DIRECT OR FROM THESE FINE DEALERS:

JOHNSON COMPUTER	PLAINSMAN MICROSYSTEMS	ARESCO	LONG ISLAND COMPUTER GENERAL STORE	LONE STAR ELECTRONICS
Box 523	Box 1712	P.O. Box 43	103 Atlantic Avenue	Box 488
Medina, Ohio 44256	Auburn, Ala. 36830	Audubon, Pa. 19407	Lynbrook, N.Y. 11563	Manchaca, Texas 78652
216-725-4560	800-633-8724	215-631-9052	516-887-1500	512-282-3570

PONG SOUND EFFECTS

George W. Hawkins, NY

Those of you who have purchased The First Book of KIM may have noticed the Ping Pong program on page 95. Did you also notice that something was missing? If you enter the bytes 20 59 03 EA starting at address 02E9, enter the bytes 20 73 03 starting at address 031A, rig up PA0 for audio output, and add the modification given below, then the program will have BEEP, BOOP, and ZONK sound effects much like the commercial versions.

```
****                    .LOC   00,89
0089  XX          MEMY  XX,
008A  XX          CNT   XX,
008B  XX          PNT   XX,

****                    .LOC   03,59
0359  A5 84       MBEP  LDA Z  84,
035B  F0 13             BEQ R  RTN    NO SOUND IF GAME OVER
035D  08                PHP
035E  A9 02             LDA I  02,    MISSED THE BALL BEEP
0360  85 89             STA Z  MEMY   FREQUENCY COMPENSTTION
0362  A9 80             LDA I  80,    FREQUENCY
0364  85 8A             STA Z  CNT    DURATION
0366  20 BA 03          JSR A  ENTN   PRODUCE NOTE
0369  A9 FF             LDA I  FF,    NO BEEP, OR BOOP AFTER A ZONK
036B  85 8B             STA Z  PNT
036D  A5 84             LDA Z  84,
036F  28                PLP
0370  A2 04       RTN   LDX I  04,
0372  60                RTS

0373  E6 8B       HBEP  INC Z  PNT    CHECK FOR LAST MOVE A ZONK
0375  F0 21             BEQ R  BACK   YES
0377  A5 84             LDA Z  84,    HIT, OR SERVE BEEP, GET DIRECTION
0379  F0 1D             BEQ R  BACK   NO SOUND IF GAME OVER
037B  30 0E             BMI R  LBEP   LEFT, OR RIGHT?
037D  A9 08             LDA I  08,
037F  85 89             STA Z  MEMY   FREQUENCY COMPENSATION
0381  85 8A             STA Z  CNT    DURATION
0383  A9 20             LDA I  20,    FREQUENCY
0385  20 BA 03          JSR A  ENTN
0388  4C 98 03          JMP A  BACK

038B  A9 04       LBEP  LDA I  04,
038D  85 87             STA Z  MEMY
038F  A9 08             LDA I  08,
0391  85 8A             STA Z  CNT
0393  A9 40             LDA I  40,
0395  20 BA 03          JSR A  ENTN

0398  A5 84       BACK  LDA Z  84,    GET DURATION FOR ORIGINAL REVERSE
039A  18                CLC           AND CLEAR CARRY
039B  60                RTS

                                      TONE GENERATOR LOOP
                                      PARAMS:
                                      A=FREQUENCY
                                      MEMY=FREQUENCY DURATION COMPENSATION
                                      CNT=DURATION
039C  AA          CLK   TAX           MOVE FREQUENCY TO X
039D  EE 00 17          INC A  UPA    TOGGLE OUTPUT PIN 14
03A0  CA          DLX   DEX           DECREMENT X
03A1  F0 07             BEQ R  COMP   REPEAT TIMES COMPENSATION IF ZERO
03A3  EA                NOP           WAIT OTHERWISE
03A4  EA                NOP
03A5  EA                NOP
03A6  EA                NOP
03A7  EA                NOP
03A8  D0 F6             BNE R  DLX    DELAY FOR FREQUENCY
03AA  88          COMP  DEY           DECREMENT Y (FREQUENCY COMPENSATION)
03AB  F0 12             BEQ R  DUR    CHECK DURATION IF ZERO
03AD  EA                NOP           LOOP TIMING
03AE  EA                NOP
03AF  EA                NOP
03B0  EA                NOP
03B1  D0 00             BNE R  ON
03B3  D0 E7       ON    BNE R  CLK    KEEP TONE GOING
                                      ENTRY FOR REST
03B5  A2 00       RDUR  LDX I  00,    INITIALIZE PORT FOR SILENCE.  USE A14.
03B7  4C BC 03          JMP A  DUR1
                                      ENTRY FOR NOTE
03BA  A2 01       ENTN  LDX I  01,    INITIALIZE PORT FOR NOTE.  USE A14.
03BC  8E 01 17    DUR1  STX A  UPAD
03BF  C6 8A       DUR   DEC Z  CNT    DECREMENT DURATION
03C1  F0 04             BEQ R  DONE   RETURN IF ZERO
03C3  A4 89             LDY Z  MEMY   GET FREQUENCY COMPENSATION
03C5  D0 D5             BNE R  CLK    KEEP TONE GOING YET
03C7  60          DONE  RTS           RETURN
```

AIM 65 BY ROCKWELL INTERNATIONAL



AIM 65 is fully assembled, tested and warranted. With the addition of a low cost, readily available power supply, it's ready to start working for you.

AIM 65 features on-board thermal printer and alphanumeric display, and a terminal-style keyboard. It has an addressing capability up to 65K bytes, and comes with a user-dedicated 1K or 4K RAM. Two installed 4K ROMS hold a powerful Advanced Interface Monitor program, and three spare sockets are included to expand on-board ROM or PROM up to 20K bytes.

An Application Connector provides for attaching a TTY and one or two audio cassette recorders, and gives external access to the user-dedicated general purpose I/O lines.

Also included as standard are a comprehensive AIM 65 User's Manual, a handy pocket reference card, an R6500 Hardware Manual, an R6500 Programming Manual and an AIM 65 schematic.

AIM 65 is packaged on two compact modules. The circuit module is 12 inches wide and 10 inches long, the keyboard module is 12 inches wide and 4 inches long. They are connected by a detachable cable.

THERMAL PRINTER
Most desired feature on low-cost microcomputer systems . . .
- Wide 20-column printout
- Versatile 5 x 7 dot matrix format
- Complete 64-character ASCII alphanumeric format
- Fast 120 lines per minute
- Quite thermal operation
- Proven reliability

FULL-SIZE ALPHANUMERIC KEYBOARD
Provides compatibility with system terminals . . .
- Standard 54 key, terminal-style layout
- 26 alphabetic characters
- 10 numeric characters
- 22 special characters
- 9 control functions
- 3 user-defined functions

TRUE ALPHANUMERIC DISPLAY
Provides legible and lengthy display . . .
- 20 characters wide
- 16-segment characters
- High contrast monolithic characters
- Complete 64-character ASCII alphanumeric format

PROVEN R6500 MICROCOMPUTER SYSTEM DEVICES
Reliable, high performance NMOS technology . . .
- R6502 Central Processing Unit (CPU), operating at 1 MHz. Has 65K address capability, 13 addressing modes and true index capability. Simple but powerful 56 instructions.
- Read/Write Memory, using R2114 Static RAM devices. Available in 1K byte and 4K byte versions.
- 8K Monitor Program Memory, using R2332 Static ROM devices. Has sockets to accept additional 2332 ROM or 2532 PROM devices, to expand on-board Program memory up to 20K bytes.
- R6532 RAM-Input/Output-Timer (RIOT) combination device. Multipurpose circuit for AIM 65 Monitor functions.
- Two R6522 Versatile Interface Adapter (VIA) devices, which support AIM 65 and user functions. Each VIA has two parallel and one serial 8-bit, bidirectional I/O ports, two 2-bit peripheral handshake control lines and two fully-programmable 16-bit interval timer/event counters.

BUILT-IN EXPANSION CAPABILITY
- 44-Pin Application Connector for peripheral add-ons
- 44-Pin Expansion Connector has full system bus
- Both connectors are KIM-1 compatible

TTY AND AUDIO CASSETTE INTERFACES
Standard interface to low-cost peripherals . . .
- 20 ma. current loop TTY interface
- Interface for two audio cassette recorders
- Two audio cassette formats: ASCII KIM-1 compatible and binary, blocked file assembler compatible

ROM RESIDENT ADVANCED INTERACTIVE MONITOR
Advanced features found only on larger systems . . .
- Monitor-generated prompts
- Single keystroke commands
- Address independent data entry
- Debug aids
- Error messages
- Option and user interface linkage

ADVANCED INTERACTIVE MONITOR COMMANDS
- Major Function Entry
- Instruction Entry and Disassembly
- Display/Alter Registers and Memory
- Manipulate Breakpoints
- Control Instruction/Trace
- Control Peripheral Devices
- Call User-Defined Functions
- Comprehensive Text Editor

LOW COST PLUG-IN ROM OPTIONS
- 4K Assembler—symbolic, two-pass
- 8K BASIC Interpreter

POWER SUPPLY SPECIFICATIONS
- +5 VDC ± 5% regulated @ 2.0 amps (max)
- +24 VDC ±15% unregulated @ 2.5 amps (peak) 0.5 amps average

PRICE: $375.00 (1K RAM)

Plus $4.00 UPS (shipped in U.S. must give ***street*** address), $10 parcel post to APO's, FPO's, Alaska, Hawaii, Canada, $25 air mail to all other countries

We manufacture a complete line of high quality expansion boards. Use reader service card to be added to our mailing list, or U.S. residents send $1.00 (International send $3.00 U.S.) for airmail delivery of our complete catalog.

RNB ENTERPRISES
INCORPORATED

2967 W. Fairmount Avenue
Phoenix AZ. 85017
(602)265-7564

master charge VISA

BASEBALL FOR THE KIM by Robert Leedom

(Editors note-Bob Leedom, author of Hexpawn, presents another real cute diversion for the basic KIM. Stuff like this still really excites me. I don't usually like to publish hex dumps because they are so frustrating to find your way through them, but for those of you who want to see what makes Baseball tick, you can get copies of the listing-see the ad for User Notes cassettes.)

A video style action game for the KIM-1, which uses the on board LED displays in three ways.

1. You see the windup, the pitch (one of six) and the swing.

KEY	PITCH
0	SLOW BALL
1	FAST BALL
2	UP CURVE
3	DOWN CURVE
4	RISER
5	SINKER



2. You see the hit (if the pitcher was able to get the ball in the strike zone, and if the batters timing was good enough)-in this case, an out-of-park home run:



...but there are also six kinds of hits!

3. You see everything you need to know about the game's progress: naturally, you'll see the umpire's calls and score, but you'll also see, just before each pitch (or at the touch of the 'PC' key during windup), a compact status display. The score may be seen during windup by pressing the '+' key.



The game can be played as nine-innings worth of batting practice against KIM's pitching, or as a two player game. In batting practice, the 'team at bat' display will be blanked (of course, if the two of you are tied at the end of nine innings, the game will go into extra innings (E on the inning # display) until there's a winner!). The KIM keyboard serves as the input for pitch selection and for batting, but for about $3 worth of Radio Shack switches, you can "remote" the pitchers' and/or the batters controls! And only two data words are necessary to support these changes.

Control Word	Value of Control Word	Batting and Pitching inputs
BATTER (loc. $002B)	Positive or Zero*	Batter uses Keyboard ("B"-key)
	Negative	Batter uses remote pushbutton switch.
PITCHER (loc. $002C)	Positive	Pitcher uses keyboard (keys 0-5)
	Zero*	Computer pitches
	Negative	Pitcher uses remote rotary and pushbutton switches

*VALUE SET ON PROGRAM TAPE

KIM gives you a slight edge-if you're quick enough to pass up a fourth wild pitch for a walk, all your baserunners will advance. But the quality of pitching's pretty good-be on your toes!

REMOTE PITCH/BAT FOR KIM-1 BASEBALL



S1 SWITCH POSITION	SELECTED PITCH
1 , 7	SLOW BALL
2 , 8	FAST BALL
3 , 9	UP CURVE
4 , 10	DOWN CURVE
5 , 11	RISER
6 , 12	SINKER

PARTS LIST

S1 single pole, 12 position switch (Radio Shack 275-1385, $.99)

S2, S3 SPST switch, normally closed (Radio Shack 275-1548, 5 for $2.49)

I mounted S1 and S2 in what I call the Pitchers' Wand, a Head & Shoulders plastic shampoo bottle. (The neck of the bottle is the handle, and S1 is where the label was. S2 can be easily flicked with the thumb while holding the handle.) The reason for the 12-position PITCH SELECT switch is to make it harder for the batter to memorize switch positions and listen to clicks-for example, one click from a slow ball can either be a fastball or a sinker.

S3 was mounted in a small plastic pill bottle that fits easily into the hand.

Start Baseball at $0200. To restart the game, hit GO during the windup or during the the endgame display (six baseballs).

0000-03FF & 1780-17E6

```
000  00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00
010  00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00
020  00 00 00 00 00 00 00 00 08 40 01 01 00 FD 00 00
030  00 FE 01 FF 02 03 A4 9F AF B5 BB C1 A9 8D 87 6F
040  75 00 01 40 41 08 09 48 49 3A 1A 2A 2A 25 2F 3A
050  1A 2A 2A 25 2F 20 20 24 24 29 2E 2F AA AA AF A5
060  A9 AB FA 5A FF 55 F9 5B 29 2D 2F 2A 2F 2B 2B 00
070  00 78 5C 00 00 00 00 50 1C 54 6D 7C 77 38 38 00
080  00 6D 78 50 00 00 00 39 77 3E 3D 76 78 37 06 6D
090  6D 79 5E 6E 79 50 5C 1C 78 00 00 00 5C 1C 78 73
0A0  3F 73 3E 73 00 71 3F 3E 38 00 76 3F 37 79 50 71
0B0  38 6E 5C 1C 78 6D 04 54 3D 38 79 5E 5C 1C 7C 38
0C0  79 78 50 04 73 38 79 5E 7C 38 00 73 38 63 63 63
0D0  63 63 63 46 13 D0 04 A9 20 85 13 20 63 01 A5 13
0E0  85 24 A9 30 85 1F A0 07 20 17 01 88 D0 FA 60 73
0F0  18 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00

100  B4 26 A0 05 B1 26 99 1F 00 88 10 F8 A0 C0 20 17
110  01 20 17 01 88 D0 F7 84 25 A0 00 A9 7F 8D 41 17
120  A2 09 84 FC B9 1F 00 20 4E 1F C8 C0 06 90 F3 20
130  3D 1F 20 6A 1F A4 25 60 EA 85 0B B5 49 48 48 29
140  F8 EA 85 1D 4A 85 07 68 29 03 85 F4 68 4A 4A 29
150  03 85 F3 B5 5C A2 03 48 29 03 95 EF 68 4A 4A CA
160  10 F5 60 A9 00 A2 05 95 1F CA 10 FB A6 0B B4 EF
170  B9 27 00 95 1F A4 1D 60 A2 00 46 1A 90 1C A6 00
180  B5 11 69 00 95 11 E0 0B D0 10 A5 01 C9 09 90 0A
190  A5 1B C5 1C B0 04 86 1E D0 06 88 10 DD 8A F0 23
1A0  A5 1B 20 80 17 A6 2C F0 11 84 6F 85 70 A5 1C 20
1B0  80 17 84 73 85 74 A0 6F D0 06 84 75 85 76 A0 75
1C0  20 00 01 60 84 09 98 D8 C5 07 90 04 A5 1D E5 09
1D0  A2 08 86 13 C5 07 90 0A E5 07 48 A5 12 05 13 85
1E0  12 68 46 07 46 13 D0 EC A6 12 B5 2D 60 60 17 A4
1F0  AA 17 A4 AA 70 1F 70 1F 70 00 00 00 98 00 35 00

200  AD 06 17 85 15 F8 A9 0B 85 00 A9 00 85 1E 85 01
210  85 1B 85 1C A5 00 49 01 85 00 C9 0A D0 07 18 A5
220  01 69 01 85 01 A9 00 85 02 85 1A A9 00 85 04 85
230  05 A5 1A 09 08 85 1A A9 00 85 12 85 13 A9 05 85
240  0B 20 D3 03 A5 2C F0 24 A5 2C 10 10 20 C4 17 4A
250  90 12 29 1F A2 00 4A 90 32 E8 10 FA 20 2F 01 C9
260  06 AA 90 27 20 D3 00 20 91 17 B0 DC 20 AD 17 29
270  7F 09 20 85 08 20 D3 00 20 91 17 C6 08 D0 F6 20
280  AD 17 29 07 C9 06 90 02 E9 06 AA 20 AD 17 29 07
290  C9 03 B0 0D A8 8A D0 03 98 D0 06 E8 E8 E8 E8 E8
2A0  E8 20 3B 01 A9 FF 85 03 A9 30 85 0A 20 63 01 20
2B0  17 01 A6 03 10 18 C9 11 F0 09 A5 2B 10 10 20 C4
2C0  17 10 0B A9 06 85 0A A5 1F 0A 30 41 85 03 A5 1F
2D0  29 49 05 0A 85 1F 88 D0 D6 A5 03 10 2D C6 0B 10
2E0  CB A5 EF C9 02 F0 23 E6 04 A6 04 BD E7 1F 85 80
2F0  A0 7B 20 00 01 A5 04 C9 04 D0 6E A0 00 20 78 01

300  A5 1E F0 03 4C 9C 03 4C 2B 02 4C 6C 03 20 C4 01
310  85 06 18 69 0F AA F8 A9 01 20 39 01 20 63 01 A9
320  06 85 1F 20 17 01 88 D0 FA E6 0B A5 0B C9 06 D0
330  EB A6 06 B4 39 20 00 01 A9 00 85 09 20 AD 17 29
340  04 F0 02 E6 09 A4 06 10 B4 C8 D0 03 4C CD 17 A6
350  09 D0 03 C8 30 0D B4 3D 20 00 01 A6 09 86 06 F0
360  D2 D0 22 A5 05 C9 02 D0 03 4C 37 02 E6 05 A6 05
370  BD E7 1F 85 86 A0 81 20 00 01 A5 05 C9 03 D0 E9
380  A0 93 20 00 01 E6 02 A6 02 BD E7 1F 85 9A A0 99
390  20 00 01 A5 02 C9 03 F0 03 4C 2B 02 20 A0 01 A5
3A0  1E D0 26 A5 01 C9 09 B0 07 A5 2C D0 13 4C 1E 02
3B0  A5 2C F0 15 A5 00 C9 0B F0 09 A5 1B C5 1C 90 09
3C0  4C 14 02 A5 1B C5 1C F0 F7 20 91 17 A0 CD 20 00
3D0  01 F0 C9 A2 05 B4 00 B9 E7 1F 95 0C CA 10 F6 A5
3E0  01 C9 0A 90 04 A9 79 85 0D A5 1A 29 07 AA B5 41
3F0  85 0F A5 2C D0 04 A9 00 85 0C A0 0C 4C 00 01 B3

1780 48 4A 4A 4A 4A AA BC E7 1F 68 29 0F AA BD E7 1F
1790 60 20 17 01 C9 20 D0 03 20 D3 03 C9 1B D0 03 20
17A0 A0 01 C9 19 D0 05 68 68 4C 05 02 38 60 38 D8 A5
17B0 15 65 16 65 19 85 14 A0 04 B9 14 00 99 15 00 88
17C0 10 F7 F8 60 A9 00 8D 01 17 AD 00 17 60 A5 1A 0A
17D0 05 02 C9 18 F0 04 C9 14 D0 09 A0 C7 20 00 01 84
17E0 1A E6 02 4C B5 03 FF 00 00 00 00 00 00 00 00 00
```

LANGUAGE LAB

basic

AN EDITOR FOR MICROSOFT BASIC

from Sean McKenna
64 Fairview Ave
Piedmont CA 94610

(Editors note: How many times have you had to reenter a whole line in a Basic program just to correct one small typo? No need for that aggravation any longer. Sean is generously sharing the editor portion of his Basic Enhancements Package with us).

Character oriented editor for KIM BASIC:

1) Set the BASIC I-O calls and the I-O calls to your system as indicated in the listing.

2) The delimiter is set by the contents of $02CB (it is a backslash although appears as a ¢ in the program due to printer strangeness)

3) The command is set by the contents of $0214 to be ")" in the first position of an input line.

4) Before making any use of the program, FIXFLG and INDEX ($00ED and $00E3) must be initialized to $00.

5) To edit a program type the command ")" followed by any valid line number, backslash, material to be deleted, backslash, material to be added, backslash, CR. If the edit goes well you will get the usual "OK" prompt. If the string you specified for editing was not found you will get a "MATCH ERROR". If the addition asked for caused a line overflow you will get a "TOO LONG ERROR". If you neglect to include all three delimiters you will get a "SYNTAX ERROR". In all error situations the original line remains intact. You may delete material by not putting anything between the 2nd and 3rd delimiters. You may move a line be doing an edit on the line number itself and then deleting the original line. Line and character delete (@ and _) will operate as usual during an edit line input.

```
0060: 0200            FIXIN  ORG   $0200
0070: 0200            FIXFLG *     $00ED
0080: 0200            INDEX  *     $00E3
0090: 0200            PLACE  *     $00E8
0100: 0200            POINT  *     $00E1
0110: 0200            LENGTH *     $00E9
0120: 0200            LIMIT  *     $00E5
0130: 0200            TERMNL *     $0017
0140: 0200            CRCONT *     $00E4
0150: 0200            YTEMP  *     $00E0
0160: 0200            BASBUF *     $001B
0170: 0200            MATCH  *     $0110
0180: 0200            BASERX *     $2321
0190:
0200:                    * * * * * * * * * * * * * * *
0210:                    BASIC Input call from $2456 to here
0220:                    * * * * * * * * * * * * * * *
0230: 0200 24 ED            BIT   FIXFLG  IF fix flag set
0240: 0202 10 07            BPL   GETIN
0250: 0204 E6 ED            INCZ  FIXFLG  THEN clear it,
0260: 0206 A6 E8            LDXZ  PLACE   set X to end of line,
0270: 0208 A9 0D      CRRET  LDAIM $0D     and return to BASIC with a CR
0280: 020A 60         RETURN RTS
0290:                    * * * * * * * * * * * * * * *
0300: 020B 20 C0 17   GETIN  JSR   $17C0   Call to your own input routine
0310:                    * * * * * * * * * * * * * * *
0320: 020E C9 0D            CMPIM $0D     IF user input is not a CR
0330: 0210 D0 F8            BNE   RETURN  THEN return to BASIC
0340: 0212 A5 1B            LDAZ  BASBUF  ELSE IF first character in
0350: 0214 C9 29            CMPIM ')      BASIC input buffer is not ")"
0360: 0216 D0 F0            BNE   CRRET   THEN return to BASIC
```

```
OK
LIST

 10 abcdefghijklmnop
 20 qrstuvwxyz
 30 All the king's horses and all the king's men
 40 Couldn't put Humpty together again
OK
(1) ) 10¢defg¢DEFG¢

OK

(2) ) 30¢king's ¢¢

OK

LIST

 10 abcDEFGhijklmnop
 20 qrstuvwxyz
 30 All the horses and all the king's men
 40 Couldn't put Humpty together again
OK
(3) ) 40¢king's¢queen's¢

?MATCH ERROR
OK

(4) ) 30¢king's¢queen's

?SYNTAX ERROR
OK
(5) ) 30¢king's¢king's and duke's and bishop's and page's¢

?TOO LONG ERROR
OK
(6) )30¢king's¢queen's¢

OK

(7) )30¢30¢50¢

OK
LIST

 10 abcDEFGhijklmnop
 20 qrstuvwxyz
 30 All the horses and all the queen's men
 40 Couldn't put Humpty together again
 50 All the horses and all the queen's men
OK
```

```
0370: 0218 C6 ED          DECZ  FIXFLG  ELSE set flags for input and
0380: 021A C6 E3          DECZ  INDEX   output routines,
0390: 021C 86 E5          STXZ  LIMIT   save X for buffer check
0400: 021E A9 00          LDAIM $00     clear all counters
0410: 0220 AA             TAX
0420: 0221 A8             TAY
0430: 0222 85 E8          STAZ  PLACE
0440: 0224 85 E0          STAZ  YTEMP
0450: 0226 20 C3 02 FNDPOS JSR  DELIMI  find start of edit string
0460: 0229 D0 FB          BNE   FNDPOS
0470: 022B 86 E1          STXZ  POINT   and save X for end of routine
0480: 022D 20 C3 02 ESTRNG JSR  DELIMI  save edit string in match
0490: 0230 F0 06          BEQ   NEWSTG
0500: 0232 99 10 01       STAAY MATCH
0510: 0235 C8             INY
0520: 0236 D0 F5          BNE   ESTRNG
0530: 0238 88       NEWSTG DEY
0540: 0239 84 E9          STYZ  LENGTH  save length of edit string
0550: 023B C8             INY
0560: 023C 20 C3 02 NEXNEW JSR  DELIMI  save new string in match
0570: 023F F0 06          BEQ   OVER
0580: 0241 99 10 01       STAAY MATCH
0590: 0244 C8             INY
0600: 0245 D0 F5          BNE   NEXNEW
0610: 0247 A9 0D    OVER  LDAIM $0D
0620: 0249 99 10 01       STAAY MATCH
0630: 024C A9 04          LDAIM $04     set counter for output
0640: 024E 85 E4          STAZ  CRCONT
0650: 0250 A9 99          LDAIM $99     put LIST token at start of buffer
0660: 0252 85 1B          STAZ  BASBUF
0670: 0254 A6 E1          LDXZ  POINT   put pointer in X
0680: 0256 D0 B0          BNE   CRRET   and return to BASIC with a CR
0690:
0700:
0710: 0258 A5 E4    COUNTR LDAZ  CRCONT  IF counter=0
0720: 025A D0 0F          BNE   NOTHRU
0730: 025C E6 E3          INCZ  INDEX   THEN clear flag
0740: 025E A9 0D          LDAIM $0D
0750: 0260 24 E9          BIT   LENGTH  check that string was found
0760: 0262 30 05          BMI   FOUND
0770: 0264 A2 AB          LDXIM $AB     "mismatch" error exit
0780: 0266 4C 21 23       JMP   BASERX
0790: 0269 D0 07    FOUND BNE   GOOUT
0800: 026B C6 E4    NOTHRU DECZ  CRCONT  ELSE decrement counter
0810: 026D 60             RTS           and return
0820:
0830:                  * * * * * * * * * * * * * * * *
0840:                  BASIC output call from $2A51 to here
0850:                  * * * * * * * * * * * * * * * *
0860: 026E 24 E3    FIXOUT BIT   INDEX   IF flag clear
0870: 0270 30 03          BMI   DOFIX
0880:                  * * * * * * * * * * * * * * * *
0890: 0272 4C 17 10 GOOUT  JMP   $1017    Call your own output routine
0900:                  * * * * * * * * * * * * * * * *
0910: 0275 C9 0D    DOFIX CMPIM $0D     ELSE IF CR
0920: 0277 F0 DF          BEQ   COUNTR  THEN go check counter
0930: 0279 C9 0A          CMPIM $0A     ELSE IF LF
0940: 027B F0 DB          BEQ   COUNTR THEN ditto
0950: 027D 86 E1          STXZ  POINT   ELSE save X
0960: 027F A4 E0          LDYZ  YTEMP   load indexes
0970: 0281 A6 E8          LDXZ  PLACE
0980: 0283 24 E9          BIT   LENGTH
0990: 0285 30 0C          BMI   NOMATC
1000: 0287 D9 10 01       CMPAY MATCH   IF character match
1010: 028A D0 07          BNE   NOMATC
1020: 028C C4 E9          CPYZ  LENGTH  THEN if length match
1030: 028E F0 0F          BEQ   EDIT
1040: 0290 C8             INY
1050: 0291 D0 02          BNE   CONTIN
1060: 0293 A0 00    NOMATC LDYIM $00
1070: 0295 20 B2 02 CONTIN JSR   BUMP
1080: 0298 86 E8    CLOSE STXZ  PLACE   save and restore registers
1090: 029A 84 E0          STYZ  YTEMP
1100: 029C A6 E1    EROUT LDXZ  POINT
1110: 029E 60             RTS
1120: 029F E8       EDIT  INX

1130: 02A0 CA       DELETE DEX          do delete
1140: 02A1 C6 E9          DECZ  LENGTH
1150: 02A3 10 FB          BPL   DELETE
1160: 02A5 C8       INSERT INY          and insert
1170: 02A6 B9 10 01       LDAAY MATCH
1180: 02A9 C9 0D          CMPIM $0D
1190: 02AB F0 EB          BEQ   CLOSE   till done
1200: 02AD 20 B2 02       JSR   BUMP
1210: 02B0 D0 F3          BNE   INSERT
1220:

1230: 02B2 95 1B    BUMP  STAZX BASBUF  Inserts character in buffer
1240: 02B4 E8             INX           checking for overflow
1250: 02B5 E4 17          CPXZ  TERMNL  IF line too long
1260: 02B7 90 09          BCC   CLEAR
1270: 02B9 A9 00          LDAIM $00     clear pending input line
1280: 02BB 85 1B          STAZ  BASBUF
1290: 02BD A2 B7          LDXIM $B7     "too long" error exit
1300: 02BF 4C CF 02       JMP   ERROR
1310: 02C2 60       CLEAR RTS
1320:

1330: 02C3 E8       DELIMI INX          looks for delimiter and checks
1340: 02C4 E4 E5          CPXZ  LIMIT   for complete command
1350: 02C6 10 05          BPL   SYNERR
1360: 02C8 B5 1B          LDAZX BASBUF
1370: 02CA C9 5C          CMPIM '¢
1380: 02CC 60             RTS
1390:
1400: 02CD A2 10    SYNERR LDXIM $10    "syntax" error exit
1410: 02CF E6 E3    ERROR INCZ  INDEX   resets flags
1420: 02D1 E6 ED          INCZ  FIXFLG
1430: 02D3 4C 21 23       JMP   BASERX  and returns to BASIC via error entry
```

It boggles the mind to think about what Sean could do if he had a source listing to work from..... Eric

SOME BASIC HINTS FROM

Bob Kurtz
Micro-Z Electronic Systems
Box 2426
Rolling Hills CA 90274

A. Several articles have been written about programs in BASIC that provide a word processor or text editor capability. Unfortunately, BASIC uses the comma (,) and the colon (:) as commands, and if they appear in the text that you are writing - BASIC will immediately reply with an error statement. The following POKE instructions, placed early in your program, will de-activate these commands:

```
XXXX  POKE 11031,34:POKE 11035,34
```

At the end of the program, insert the following instructions to put BASIC back the way it was:

```
ZZZZ  POKE 11031,58:POKE 11035,44
```

B. Some versions of KIM BASIC will not execute the SPC command properly-but will execute it the same as the TAB command. The reason is that there was a CLC instruction improperly located. Make the following changes:

```
298B  18          298E  C9
298C  F0          298F  2C
298D  67
```

This will permit the SPC(X) instruction to space over X units from the last location on the terminal-not form the left margin.

BASIC NOTE

from Sean McKenna
64 Fairview Ave
Piedmont CA 04610

In issue #31 of Dr. Dobb's Journal there was a machine language renumber program for PET BASIC. In the current issue (#36) there are notes indicating changes which allow the program to work for KIM BASIC. Relative to the other renumbering programs which have appeared in the notes this is a vast improvement: it changes decimal numbers in a line only immediately following a GOTO, GOSUB, THEN, or ON; it will accomodate a change from any size number to any other size without any special consideration such as leaving spaces, etc.; it is very FAST, naturally. The program also revealed some interesting aspects of BASIC's mysterious inner workings which may be useful in other contexts.

PRODUCT REVIEW by the Editor

MICROSOFT BASIC ENHANCEMENTS

If you're bothered by the fact that Microsoft Basic doesn't have an automatic line number feature, a line editor, or a renumbering command, then you're in luck. Sean McKenna who shared his Basic auto-line number with us in issue #14 has come up with a dynamite mod package for the 9 digit Basic (will work with the package from Johnson Computer or Micro-Z).

This 1.25K package is written in machine code and includes the auto line number command, a renumber feature, a line editor, an append program capability and a controlled output (outputs 16 line and waits for user input). All in all, a really nice package that worked right the first time I loaded it in. By the way, getting this package interfaced to Basic was no sweat at all-since this package interfaces itself to Basic!

All that's necessary, once both programs are loaded,to start running at an address contained in the mod package. The mod package hooks itself into Basic and then jumps to Basics initialization routine. Really clean.

This mod package consists of a cassette, and a 20 page manual which includes a complete source listing (!). It sells for $20 (plus $1.50 S&H) and is available from Sean McKenna, 64 Fairview Ave., Piedmont CA 94610.

A fair price for some powerful Basic enhancements.

Eric

focal

First of all, I want to thank Dave and Don Marsh from the 6502 Program Exchange (2920 Moana Ln., Reno NV 89509) for providing me with the source listing for their version of FCL-65E. The listing has been invaluable in getting all the mods set up for both versions of FOCAL (one from Aresco and the other from the Program Exchange).

By the way, both versions must be suitably modified as per issue #14 in order to use the modifications that will be presented. Program Exchange FCL-65E users need to move the start up message at line 00.00 to the top of the 8K block by moving the data at $35D4 through $35F3 to start at $3FE0.

In trying to cooordinate these mods across two versions of FOCAL, I've run across a zero-page usage problem in the Program Exchange versions. This version uses about 50 bytes of zero-page for terminal I/O. (According to the exchange, this was done to make FOCAL more portable between different machines). Anyhow, the long and short of it is - these I/O routines will have to be moved back into FOCAL to allow freer use of zero page.

Once the line 0.0 has been moved up to the top of the 8K block, the I/O routines from $00A9-$00DC can be moved to start at location $35D4. Of course, the internal references to OUT and IN will have to be changed to reflect the changes.

FOCAL ENHANCEMENT PACKAGE

The 'NOTES' is now distributing a very useful FOCAL enhancement package that will let you save and load complete FOCAL programs on cassette as well as lines or groups of lines and/or program variables. Commands may also be executed directly from cassette. The package was written by Joe Woodard. For ordering info, see the cassette software ad in this issue.

ADDING A CASSETTE INTERFACE AND A USER FUNCTION TO 6502 PROGRAM EXCHANGE'S FOCAL 65-E

by William C. Clements, Jr.
1489 51ST Ave East
Tuscaloosa Al 35404

The FOCAL language is really a good alternative to BASIC, at least for KIM users. Of course, it doesn't have everything. The features I missed the most were a cassette interface and the ability to execute a machine-language routine within a FOCAL program. This article shows how to add tape Load and Keep commands and how to implement a "user" function similar to that of TINY BASIC. The modifications apply to FOCAL-65 (V3D) for the KIM-1 as supplied by the 6502 Program Exchange.

Listing 1 gives the code needed to add the cassette interface commands. I began it directly after the FOCAL interpreter, because I had moved the RAM allocation for program text and variables to another area. It can go anywhere in memory that you wish, with simple relocation and listing the addresses of routines KEEP and LOAD in FOCAL's command dispatch tables. The cassette Load command enters the regular KIM monitor at $1873, and the Keep command uses a Hypertape routine in my system; it's almost a necessity to use a cassette dump routine faster than KIM's, since the memory required to store the FOCAL program statements in ASCII form can be large.

The tape operations could have been done using the existing I-O handlers provided in FOCAL, but I preferred to use conventional commands. The form of the commands is L xx to load a file having hexadecimal i.d. "xx" and K xx to record a file with i.d. "xx" onto tape.

Readers who have program control of their tape recorders might want to use these commands inside a FOCAL program to manipulate tape files. I can only use them in the immediate execution mode, since I have to push buttons on the recorder. The KIM tape routines exit to loc. zero, which my code sets up with a jump instructin. Hitting the G key on the TTY after either tape operation is through will get you back into FOCAL. All starting and ending address for the tape files are automatically set by the routines, including the final address after loading a file.

The Keep routine uses Hypertape stored in my system at loc. $C400; the jump at location TAPOUT will need to be fixed by the user to suit his own system. The jump in loc. zero restarts FOCAL at its cold start, as that's the only way I can use it. If you want to get back into the middle of an executing FOCAL program, the jump at location JMPFOC and the data bytes at locations ADLOW and ADHIGH will have to be changed.

The "user" function works like the one in TINY BASIC; it allows user-supplied machine code to be executed as a FOCAL function. The FOCAL code to invoke it is S FUSR (a_1,a_2,a_3,a_4), where the a's are the four arguments. The first, a_1, must always be present because it is the address to which the program will jump to begin the user's code. a_2,a_3,and a_4 are optional. a_2, if present, will be evaluated and the least significant eight bits stored in the accumulator before executing the user's code. a_3 and a_4, if present, are similarly evaluated and placed in the X and Y registers, respectively. Thus up to three bytes may be transmitted directly from the FOCAL program to the machine code (more of course can be transmitted in either direction by using FOCAL's version of PEEK and POKE, the FMEM function). The arguments can be constants, simple variables, or any other legal FOCAL expressions, and as such have decimal values.

As examples, the statement S FUSR(8192,0,16,10) will cause a jump to location $2000 with zero in A, $10 in X, and $0A in Y. The statements

```
1.1 S A=100
1.2 S B=13
1.3 S FUSR(625-(A+B),,B,)
```

would jump to $200 with $0D in X. Note that there are always three commas, as FOCAL uses them to tell which argument is which. If you want the variable FUSR itself to have a numerical value after its execution such as FRAN or FABS do, you can have your machine code put that value into the floating accumulator FAC1 (locs. $80-83 - see p. 7 of the 6502 Program Exchange's listing of FOCAL 65-E). Your machine code must transfer control to loc. FPOPJ (in FOCAL) when it is ready to re-enter FOCAL, and it will return to the point in your FOCAL program where FUSR was invoked. Listing 2 gives the machine code needed for adding FUSR to FOCAL.

The changes required within the tables of the FOCAL interpreter to make it recognize K. L, and FUSR and to execute the codes in Listings 1 and 2 are given now. The format follows that of the original listing of FOCAL.

ARESCO	PROGR. EXCH		
$350B	$34F4	18	BYTE HFUSR
3527	3510	36	HBYTE FUSR
3543	352C	41	BYTE FUSR
3557	3540	4B	ASCII 'K'
3558	3541	4C	ASCII 'L'
356B	3554	36	HBYTE KEEP
356C	3555	36	HBYTE LOAD
357D	3566	04	BYTE KEEP
357E	3567	33	BYTE LOAD

```
0010  2000            ;CASSETTE INTERFACE AND USER FUNCTION MODS
0020  2000            ;FOR FOCAL FROM W. CLEMENTS 1979
0030  2000
0040  2000            ;KIM LOCATIONS
0050  2000            PACK   =$1FAC
0060  2000            ID     =$17F9
0070  2000            PREG   =$F1
0080  2000            INL    =$F8
0090  2000            SAL    =$17F5
0100  2000            SAH    =$17F6
0110  2000            EAL    =$17F7
0120  2000            EAH    =$17F8
0130  2000            LOADT  =$1873
0140  2000            VER    =$17EC
0150  2000            HYPER  =$0200          ;ADDRESS OF HYPERTAPE ROUTINE
0160  2000
0170  2000            ;FOCAL LOCATIONS
0180  2000            FOCAL  =$2000
0190  2000            GSPNDR =$29A3          ;($29B1 IN ARESCO VERSION)
0200  2000            PBADR  =$31
0210  2000            VARBEG =$3E
0220  2000            INTGER =$2F85          ;($2F93 IN ARESCO VERSION)
0230  2000            M1     =$81
0240  2000            CHAR   =$2B
0250  2000            NXIARG =$2F7B          ;($2F89 IN ARESCO VERSION)
0260  2000
0270  2000            ;MOD LOCATIONS
0280  2000                   *=$0
0290  0000            JMPCOM *=*+2           ;JUMP VECTOR IN ZERO PAGE
0300  0002            NARGS  *=*+1           ;NUMBER OF ARGS IN USR
0310  0003            SAVA   *=*+1
0320  0004            SAVX   *=*+1
0330  0005
```

```
0340  0005
0350  0005                  ;FOCAL MODS START HERE
0360  0005                        *=$35EB
0370  35EB                        .OFF 2000
0380  35EB  20 A3 29     SUB    JSR GSPNOR       ;GET NEXT BLANK CHAR
0390  35EE  20 AC 1F             JSR PACK         ;CONVERT TO HEX AND STORE
0400  35F1  20 A3 29             JSR GSPNOR       ;REPEAT FOR
0410  35F4  20 AC 1F             JSR PACK         ;NEXT DIGIT
0420  35F7  A5 F8                LDA INL
0430  35F9  8D F9 17             STA ID           ;SET TAPE ID
0440  35FC  A9 4C                LDA #$4C         ;SETUP JUMP LOCATION
0450  35FE  85 00                STA JMPCOM       ;IN ZERO PAGE
0460  3600  A9 00                LDA #0           ;CLEAR STATUS REG
0470  3602  85 F1                STA PREG RTS     ;AND RETURN
0480  3604
0490  3604  20 EB 35     KEEP   JSR SUB          ;SET ID ETC
0500  3607  A5 31                LDA PBADR        ;SET KIM
0510  3609  8D F5 17             STA SAL          ;TAPE REGISTERS
0520  360C  A5 32                LDA PBADR+1
0530  360E  8D F6 17             STA SAH
0540  3611  A5 3E                LDA VARBEG
0550  3613  8D F7 17             STA EAL
0560  3616  A5 3F                LDA VARBEG+1
0570  3618  8D F8 17             STA EAH
0580  361B  A9 00         ADRLOW LDA #<FOCAL
0590  361D  85 01                STA JMPCOM+1     ;MAKE JUMP INSTR. A
0600  361F  A9 20         ADRHI  LDA #>FOCAL      ;RETURN TO COLDSTART
0610  3621  85 02                STA JMPCOM+2
0620  3623  4C 00 02     TAPOUT JMP HYPER
0630  3626
0640  3626  AD ED 17     ENLOAD LDA VEB+1        ;SET ADDRESS AT END OF
0650  3629  85 3E                STA VARBEG       ;PROGRAM TEXT
0660  362B  AD EE 17             LDA VEB+2
0670  362E  85 3F                STA VARBEG+1
0680  3630  4C 00 20     JMPFOC JMP FOCAL        ;RETURN TO FOCAL
0690  3633
0700  3633  20 EB 35     LOAD   JSR SUB          ;SET ID ETC
0710  3636  A9 26                LDA #<ENLOAD     ;MAKE JUMP POINT TO
0720  3638  85 01                STA JMPCOM+1     ;THE REST OF THE TAPE
0730  363A  A9 36                LDA #>ENLOAD     ;LOAD ROUTINE
0740  363C  85 02                STA JMPCOM+2
0750  363E  4C 73 18             JMP LOADT        ;READ THE CASSETTE
0760  3641
0770  3641                  ;NOW FOR THE 'USR' FUNCTION
0780  3641
0790  3641  A9 4C         FUSR   LDA #$4C         ;SET UP JUMP LOC.
0800  3643  85 00                STA JMPCOM
0810  3645  20 85 2F             JSR INTGER       ;FET FIRST ARG. IN FAC1
0820  3648  85 01                STA JMPCOM+1     ;REARRANGE LOW AND HIGH ORDER
0830  364A  A5 82                LDA M1+1         ;BYTES INTO JUMP LOCATION
0840  364C  85 02                STA JMPCOM+2     ;THAT WILL EXECUTE USER CODE
0850  364E  A9 00                LDA #0           ;ZERO THE ARG. COUNTER
0860  3650  85 02                STA NARGS
0870  3652  20 7A 36             JSR USRARG       ;EVALUATE AND SAVE HOWEVER MANY
0880  3655  84 03                STY SAVA         ;ARGUMENTS ARE LEFT
0890  3657  20 7A 36             JSR USRARG
0900  365A  84 04                STY SAVX
0910  365C  20 7A 36             JSR USRARG
0920  365F  A5 02                LDA NARGS
0930  3661  F0 0E                BEQ JMPUSR       ;JUMP TO USER'S CODE IF NO MORE ARGS
0940  3663  C9 01                CMP #$1
0950  3665  F0 08                BEQ STAC         ;SET 'A'=ARG, IF ONE ARG LEFT
0960  3667  C9 02                CMP #$2
0970  3669  F0 09                BEQ STACX        ;SET 'A'=ARG1, 'X'=ARG2 IF TWO LEFT
0980  366B  C9 03                CMP #$3
0990  366D  F0 05                BEQ STACX        ;SET 'A'=ARG1, 'X'=ARG2, 'Y'=ARG3
1000  366F  A5 03         STAC   LDA SAVA         ;ARG1 IN 'A'
1010  3671  4C 00 00     JMPUSR JMP JMPCOM       ;GO DO USER'S CODE
1020  3674  A5 04         STACX  LDA SAVX
1030  3676  AA                   TAX
1040  3677  4C 6F 36             JMP STAC
1050  367A
1060  367A  A5 2B         USRARG LDA CHAR         ;GET CURRENT CHARACTER
1070  367C  C9 2C                CMP #',          ;ANOTHER ARGUMENT?
1080  367E  F0 04                BEQ GETARG       ;YES, GO GET IT
1090  3680  C9 29                CMP #')          ;END OF STATEMENT?
1100  3682  F0 06                BEQ RET          ;YES, RETURN NOW
1110  3684
1120  3684  20 7B 2F     GETARG JSR NXIARG       ;EVALUATE NEXT ARG.
1130  3687  A8                   TAY
1140  3688  E6 02                INC NARGS        ;COUNT ARGS PAST FIRST
1150  368A  60           RET    RTS              ;RETURN
1160  368B
1170  368B                       .END
```

```
2000                ;THIS ROUTINE MAKES KIMS LEDS ANOTHER
2000                ;OUTPUT DEVICE FOR FOCAL
2000                ;WRITTEN BY BERNHARD MULDER
2000                ;           MOZARTSTR 1
2000                ;           6744 KANDEL
2000                ;           WEST GERMANY
2000
2000                ;THE STARTING ADDRESS FOR THIS ROUTINE
2000                ;MUST BE PLACED INTO FOCALS OUTPUT
2000                ;DEVICE TABLE SO FOCAL KNOWS WHERE IT IS.
2000                ;
2000                ;IN THE ARESCO VERSION, PUT THE HIGH ORDER
2000                ;BYTE OF THE STARTING ADDRESS FOR THE LED
2000                ;OUTPUT ROUTINE IN LOCATION $35BB AND THE
2000                ;LOW ORDER ADDRESS IN $35CO. IN THE 6502
2000                ;PROGRAM EXCHANGE VERSION OF FCL-65E, THIS
2000                ;WOULD CORRESPOND TO LOCATIONS $35A4 AND
2000                ;$35A9 RESPECTIVELY.
2000
2000                ;TO USE THE LEDS AS AN OUTPUT DEVICE,
2000                ;SIMPLY OUTPUT TO DEVICE #2 BY
2000                ;EXECUTING 'S FODV (2)'. ALL SUBSEQUENT
2000                ;OUTPUT WILL BE SENT TO THE DISPLAYS.
2000                ;
2000                PADD    =$1741
2000                SBD     =$1742
2000                SAD     =$1740
2000
2000                ;ZERO PAGE LOCATIONS
2000                        *=$A9
00A9                SPE1    *=*+1           ;THESE TWO CELLS CONTROL THE DISPLAY
00AA                SPE2    *=*+1           ;SPEED OF KIMS 7 SEGMENT DISPLAYS
00AB                SPE3    *=*+1
00AC                SPE4    *=*+1
00AD
00AD                ;START THIS ROUTINE RIGHT AFTER THE CASSETTE
00AD                ;AND USER FUNCTION MODS
00AD
00AD                        *=$36B0
36B0                        .OFF 2000
36B0
36B0  A8            SEVS    TAY
36B1  A2 01                 LDX #$1
36B3  BD 0A 37      SEV1    LDA DISP,X
36B6  9D 09 37              STA DIS,X
36B9  E8                    INX
36BA  E0 06                 CPX #$6
36BC  D0 F5                 BNE SEV1
36BE  B9 10 37              LDA TABB,Y
36C1  8D 0F 37              STA DISP+5      ;***BEWARE***NON-ROMABLE CODE HERE!!!
36C4  A2 01         ENRY    LDX #$1
36C6  B5 A9         ENR1    LDA SPE1,X
36C8  95 AB                 STA SPE3,X
36CA  CA                    DEX
36CB  10 F9                 BPL ENR1
36CD  20 E3 36      ENR3    JSR ZEI1        ;DISPLAY
36D0  C6 AB                 DEC SPE3
36D2  D0 F9                 BNE ENR3
36D4  C6 AC                 DEC SPE4
36D6  D0 F5                 BNE ENR3
36D8  18                    CLC             ;FINISH WITH NO ERRORS
36D9  60                    RTS
36DA  A0 00         ZEI2    LDY #$0
36DC  8C 41 17              STY PADD
36DF  8C 42 17              STY SBD
36E2  60                    RTS
36E3  20 DA 36      ZEI1    JSR ZEI2        ;ALL DISPLAYS OFF
36E6  A9 7F                 LDA #$7F
36E8  8D 41 17              STA PADD
36EB  A2 09                 LDX #$9
36ED  8E 42 17      ZEI3    STX SBD
36F0  B9 0A 37              LDA DISP,Y
36F3  8D 40 17              STA SAD
36F6  98                    TYA
36F7  48                    PHA
36F8  A0 7F                 LDY #$7F
36FA  88            ZEI4    DEY
36FB  D0 FD                 BNE ZEI4        ;DELAY ABOUT 500 CYCLES
36FD  68                    PLA
36FE  A8                    TAY
36FF  C8                    INY
3700  E8                    INX
3701  E8                    INX
3702  C0 06                 CPY #$6         ;ALL DIGITS FINISHED ?
3704  D0 E7                 BNE ZEI3
3706  20 DA 36              JSR ZEI2        ;ALL OUT
3709  60            DIS     RTS             ;DIS=DISP-1
370A
370A  00            DISP    .BYTE 0,0,0,0,0,0
370B  00
370C  00
370D  00
370E  00
370F  00
3710
3710                ;HERES THE TABLE WITH THE SEVEN SEGMENT
3710                ;CODES.  ASCII CODE=TABLE INDEX
3710
3710  00            TABB    .BYTE 0,0,0,0,0,0,0,0
3711  00
3712  00
3713  00
3714  00
3715  00
3716  00
3717  00
```

HEX DUMP STARTS HERE

TO SAVE SPACE... HERE'S A HEX DUMP OF THE SEVEN SEGMENT CODE TABLE.

```
3710  00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00
3720  00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00
3730  8B 8A A2 00 B6 00 C6 82 B9 8F 64 C6 8C C0 98 D2
3740  BF 86 DB CF E6 ED FD 87 FF EF C1 C5 00 C1 00 D3
3750  00 F7 FC DB DE F9 F1 BD F6 84 9E F0 BB B7 D4 DC
3760  F3 E7 D0 ED F8 9C EA BE EE C9 00 00 00 00 00 00
3770  00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00
3780  00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00
```

tiny basic

TINY BASIC

Editors note

Several of you were apparently confused as to how to add the Tiny Basic mods from #15 to your systems. I wholeheartedly recommend you pick up the Tiny Basic Experimenters Kit mentioned in one of the articles. (It's available for $15 from 6502 Program Exchange, 2920 Moana Ln, Reno NV 89509.

MICHAEL DAY

TINY BASIC PAGE 0 MEMORY MAP
for TOM PITTMAN's TINY BASIC TB651K V.1K

0000 - 000F	UNUSED
0010 - 001F	USED IN PROTO VERSIONS ONLY
0020 - 0021	USER SPACE LOW ADDRESS
0022 - 0023	USER SPACE HIGH ADDRESS
0024 - 0025	PROGRAM END + STACK RESERVE
0026 - 0027	TOP OF GOSUB STACK
0028 - 0029	CURRENT BASIC LINE #
002A - 002B	IL PROGRAM COUNTER
002C - 002D	BASIC POINTER
002E - 002F	SAVED POINTER
0030 - 007F	INPUT BUFFER AND COMPUTATION STACK
0080 - 0081	RANDOM NUMBER SEED
0082 - 0083	VARIABLE 'A'
0084 - 0085	VARIABLE 'B'
....	....
00B4 - 00B5	VARIABLE 'Z'
00B6 - 00B7	TRANSFER WORK POINTER
00B8 - 00B9	MISC WORK REGISTER
00BA - 00BB	MISC WORK REGISTER
00BC - 00BD	TEMPORARY STORAGE REGISTER
00BE	RUN MODE FLAG
00BF	PRINT CONTROL
00C0	INPUT BUFFER POINTER
00C1	COMPUTATION STACK POINTER
00C2	2nd ½ OF STACK POINTER (ALWAYS 00)
00C3	COUNTER (USED IN PN ONLY)
00C4 - 00C5	IL XQ POINTER
00C6 - 00C7	GOSUB STACK WORK POINTER
00C8 - 00D7	USED IN SPHERE VERSIONS ONLY
00D8 - 00FF	UNUSED

There are the major use of these registers only they may be used for other purposes on an availability basis.

TVT-6/TINY BASIC INTERFACE

by Michael Allen
6025 Kimbark
Chicago IL 60637

I had a lot of trouble getting Tom Pittman's Tiny Basic to work with the KIM-1/TVT-6 combination. Now, looking back, the input and output routines included below seem fairly simple and straight-forward. So I thought I should share these with you to help those who may be making the same mistakes I was.

The T. B. version I have resides in memory locations 0200 to 0AC6. You must change six bytes within T.B. as follows;

1. Set 0207 to C7 and 0208 to 0A. This is a jump to a subroutine to input a character. The input routine saves the return address to T.B. then jumps to the SCAN program and stays there until interrupted by a strobe signal from a key being pressed on the keyboard. If the IRQ vector has been properly set to 0AD3, a character is sent to the cursor subroutine. Then a return is made to T.B. Note that a CLI (clear interrupt status) instruction was inserted in SCAN (underlined in the hex dump).

2. Set 020A to F3 and 020B to 0A. This is a jump to the output subroutine where the miscellaneous characters T.B. sends for the benefit of a teletype are trapped before falling through to the cursor subroutine.

3. Set 020F to 08. This allows T.B. to recognize the ASCII backspace.

4. Set 028C to 0E. When starting T.B. at 0200 (cold start), this byte determines how T.B. defines the lowest address of program space.

5. Also be sure to set 17FE to D3 and 17FF to 0A.

I relocated SCAN to be able to reload T.B. from tape in one load. The version of SCAN shown is from Don Lancaster's Popular Electronics article except for bytes 0BA4 and 0BCC which were changed in order to display pages 0C00 and 0D00.

The Cursor program is adapted from Don's but is much shorter as it only supports backspace and carriage return controls--all you really need with T.B. (also INPUT sets lowercase to uppercase so you don't have to shift back and forth.)

KIM's Memory map now appears thus:

0020-00B9	Used by tiny BASIC
00E8-00EE	Used by I/O routines
0200-0AC6	Tiny BASIC
0AC7-0B79	INPUT & OUTPUT Subroutines
0B7A-0BDC	SCAN
0BDD-0BFF	34 bytes for USR subroutines (I put Don Box's subscripted variable SBR's here; see KUN #5.)
0C00-0DFF	TVT-6 display area
0E00-13FF	1.5K program area

TVT6/TINY BASIC INTERFACE LISTING

```
SET 17FE = D3, 17FF = 0A

0AC7 68        INPUT   PLA LOW     SAVE ...
0AC8 85 E8             STA TEMP            RETURN ...
0ACA 68                PLA HI                      ADDRESS.
0ACB 85 E9             STA TEMP+1
0ACD BA                TSX         AND STACK ...
0ACE 86 EA             STX TEMP+2              POINTER.
0AD0 4C A7 0B          JMP SCAN

0AD3 AD 00 17  BREAK   LDA CHAR    GET CHARACTER.
0AD6 29 7F             AND #$7F    REMOVE PARITY.
0AD8 C9 61             CMP #$61    LOWER CASE LETTER?
0ADA 90 02             BCC SKIP    NO; SKIP AHEAD.
0ADC E9 20             SBC #$20    YES; MAKE UPPER CASE.
0ADE 85 EB     SKIP    STA TEMP+3  SAVE CHARACTER.
0AE0 C9 0D             CMP #$0D    CARRAGE RETURN?
0AE2 F0 03             BEQ RTN1    YES; RETURN.
0AE4 20 FB 0A          JSR CURSOR  NO; ENTER CHARACTER.
0AE7 A6 EA     RTN1    LDX TEMP=3  RESTORE ...
0AE9 9A                TXS                 STACK POINTER.
0AEA A5 E9             LDA TEMP+1  RESTORE ...
0AEC 48                PHA                     RETURN ...
0AED A5 E8             LDA TEMP                        ADDRESS.
0AEF 48                PHA
0AF0 A5 EB             LDA TEMP+3    GET CHARACTER.
0AF2 60        RTN2    RTS           RETURN TO TINY.

0AF3 C9 0B     OUTPUT  CMP #$0B      TRAP ...
0AF5 30 FB             BMI RTN2            CONTROL ...
0AF7 C9 7F             CMP #$7F                    CHARACTERS.
0AF9 B0 F7             BCS RTN2
0AFB 48        CURSOR  PHA           SAVE CHARACTER.
0AFC A0 00             LDY #0        RESET INDEX.
0AFE A5 EE             LDA EE        GET CURSOR HI ADDR.
0B00 C9 0D             CMP #$0D      IS CURSOR ON PAGE 0D?
0B02 F0 04             BEQ CONT      YES; CONTINUE.
0B04 C9 0C             CMP #$0C      NO; OR ON PAGE 0C?
0B06 D0 2F             BNE SCROLL    NO; INITIALIZE CURSOR.
0B08 B1 ED     CONT    LDA (ED),Y    GET OLD CHARACTER.
0B0A 29 7F             AND #$7F      REMOVE CURSOR.
0B0C 91 ED             STA (ED),Y    REPLACE.
0B0E 68                PLA           RECALL NEW CHARACTER.
0B0F C9 20             CMP #$20      IS IT A CHARACTER?
0B11 B0 59             BCS ENTER     YES; ENTER IT.
0B13 C9 0D             CMP #$0D      CARRAGE RETURN?
0B15 D0 0C             BNE SKIP1     NO; SKIP
0B17 A5 ED             LDA ED        YES; MOVE CURSOR ...
0B19 09 1F             ORA #$1F                TO RIGHT SIDE.
0B1B 85 ED             STA ED        AND REPLACE.
0B1D 20 61 0B          JSR INCR      INCREMENT CURSOR.
0B20 4C 6F 0B          JMP END

0B23 C9 08     SKIP1   CMP #$08      BACKSPACE?
0B25 D0 4C             BNE RESTORE   NO; CONTINUE.
0B27 C6 ED             DEC ED        YES; DECREMENT CURSOR.
0B29 A9 FF             LDA #$FF      TEST FOR PAGE ...
0B2B C5 ED             CMP ED                      UNDERFLOW.
0B2D D0 44             BNE RESTORE   O.K. TO CONTINUE.
0B2F C6 EE             DEC EE        DECREMENT PAGE.
0B31 A9 0B             LDA #$0B      TEST FOR SCREEN ...
0B33 C5 EE             CMP EE                      UNDERFLOW.
0B35 D0 3C             BNE RESTORE   O.K.
0B37 A9 00     SCROLL  LDA #0        NOT O.K.; HOME CURSOR.
0B39 85 ED             STA ED        TO 0C00
0B3B A9 0C             LDA #$0C      (UPPER LEFT OF SCREEN)
0B3D 85 EE             STA EE
0B3F A0 20     LOOP    LDY #$20      ADD OFFSET TO INDEX.
0B41 B1 ED             LDA (ED),Y    MOVE ...
0B43 A0 00             LDY #0              CHARACTER ...
0B45 20 5F 0B          JSR STORE                   UP.
0B48 D0 F5             BNE LOOP      LOOP UNTIL END OF SCREEN.
0B4A 18                CLC           CLEAR FLAG.
0B4B A9 E0     HOME    LDA #$E0      HOME CURSOR
0B4D 85 ED             STA ED          TO 0DE0
0B4F A9 0D             LDA #$0D      (LOWER LEFT OF SCREEN).
0B51 85 EE             STA EE
0B53 B0 1E             BCS RESTORE   FINISH IF FLAG SET.
0B55 A9 20     SPACE   LDA #$20      ELSE; CLEAR LAST LINE.
0B57 20 5F 0B          JSR STORE     ENTER SPACT TO ...
0B5A D0 F9             BNE SPACE        END OF LINE.
0B5C 38                SEC           SET FLAG.
0B5D B0 EC             BCS HOME      TRY AGAIN.

0B5F 91 ED     STORE   STA (ED),Y    ENTER CHARACTER.
0B61 E6 ED     INCR    INC ED        INCREMENT CURSOR.
0B63 D0 06             BNE RTN       OVERFLOW?
0B65 E6 EE             INC EE        YES; INCR CURSOR TO NEXT PAGE.
0B67 A9 0E             LDA #$0E      TEST FOR SCREEN OVERFLOW.
0B69 C5 EE             CMP EE
0B6B 60        RTN     RTS

0B6C 20 5F 0B  ENTER   JSR STORE     ENTER CHARACTER.
0B6F D0 02     END     BNE RESTORE   END OF SCREEN?
0B71 F0 C4             BEQ SCROLL    YES; SCROLL UP.
0B73 B1 ED     RESTORE LDA (ED),Y    GET CHARACTER.
0B75 09 08             ORA #$80      ADD CURSOR.
0B77 91 ED             STA (ED),Y    REPLACE.
0B79 60                RTS           RETURN TO I/O ROUTINES.
```

HEX DUMP OF RELOCATED "SCAN" PROGRAM:

```
0B7A EA 8D 84 0B 48 68
0B80 D0 00 20 00 80 69 08 C9 C0 90 F0 20 DA 0B 20 00
0B90 80 AA AD 83 0B 69 1F 8D 83 0B 8A D0 AA EA 69 C0
0BA0 20 00 80 C9 86 90 D3 AD D9 0B 49 80 30 05 8D D9
0BB0 4B A2 66 20 DA 0B 20 DA 0B 10 05 8D D9 4B A2 67
0BC0 20 1E 80 58 48 68 A9 00 8D 83 0B A9 84 8D 84 0B
0BD0 20 00 80 18 CA 30 A4 10 ED 80 B0 00 60
```

EPROM PROGRAMMERS



EP-2A SERIES

- PROGRAMS 2708 and 2716 EPROMS
- Price $59.95 Assembled and Tested
- Kit price $49.95
- Includes Connector



EP-2A-78 SERIES

- PROGRAMS 2708, 2716, 2758, TMS 2716 and TMS 2532 EPROMS
- TEXTOOL ZERO FORCE SOCKET
- Price $79.95 Assembled and Tested
- Includes Connector

Software available for the Rockwell AIM-65, MOS Technology KIM-1, Synertek SYM-1, Motorola D2, RCA VIP and many other single board computers that use the 6502, 6800, 8080/85, Z-80, 1802, F-8 and 2650 CPU's. Stock. Specify one set of software.

Optimal Technology Inc.
Blue Wood 127
Earlysville, VA 22936 U.S.A.
Phone (804) 973-5482

LONE STAR ELECTRONICS

ANNOUNCES

The K/S Converter. Run KIM (MOS Technology) Software on your SYM! For the price of a blank 2716, the K/S converter enables your SYM to:

1. READ and WRITE KIM tapes at:
   - Normal Speed
   - 2 X Normal Speed
   - 3 X Normal Speed
   - 6 X Normal Speed (HYPERTAPE)
2. Run most KIM software directly (*The First Book of KIM*, for example).

The converter comes complete with a programmed 2716 EPROM and detailed instruction for installation and use.

Send check or money order for $59.95 (or order UPS COD) To:

LONE STAR ELECTRONICS
Box 488
Manchaca, Texas 78652
(512) 282-3570



The new MORE™ board by T.T.I. is an easy to install and use expansion for the basic KIM,* AIM,** or Kim compatible micro-computer. One unique feature of this board is it's ability to program, run or copy industry standard EPROM's--2708, 2716 (+5 & +12) or 2716, 2758, TMS 2516 (+5V only). Individual program and run personality keys and software allow the user to program from RAM or copy data from any given EPROM into any other type EPROM. (Example: Empty two 2708's into one 2716!). Additionally, the board has sockets for 3K of RAM (2114's), and two zero insertion force EPROM sockets. Also featured is a 16 Bit latchable buffered output port with two dip headers for access. Associated with this port is a row of 16 LED's arranged in binary sequence. All voltages necessary to run and program the EPROMS are generated on board. Only +5 and +12 volt supplies are required. (Approximately 200 MA from each supply).

Standard 22 pin edge connectors allow the board to be plugged onto the KIM* or Kim compatible machine. All signal lines are passed through the MORE™ board and are made available in total on standard 22 pin paddle cards.

The MORE™ board and KIM* or equivalent, make a low cost and excellent dedicated controller, educational tool, hobby computer expansion or development system.

The price with prepaid shipping in U.S. is $169.95-includes 8 personality keys, documentation, and software listings. Options---software on tape for AIM** or KIM* $10.00---Software in 2708 EPROM for $30.00.

*Product of MOS Technology **Product of Rockwell

T.T.I.
P.O. Box 2328
Cookeville, TN. 38501
615-526-7579

KIMSI, S-100

16K RAM MOD

from Vince Coppola
12 Charles St.
Plantsville, CT 06479

I have installed the Digital Research S-100, 16K static RAM board sucessfully in my KIM-KIMSAI system, with only one minor modification. Remember, the board uses 2114 1Kx4 bit RAMS, so for 4K of memory all you need is 8 RAM chips. Also, the board can be depopulated to one 4K block or any multiple of 4K right on up to the full 16K. The manufacturer also states that a full blown board will draw less that 2 amps.

The modification I came up with, consists of grounding pin 75 of the board. This is done because pin 75 on the KIMSAI is not used and is therefore left floating. By grounding it and inserting the associated jumper, pin 4 of U-43 will be brought low therefore presetting the flip-flop and siabling the bank-select circuitry. Also, the enable LED should now stay always lit.

(EDITORS' NOTE-Vince also told me a little about the CGRS disk system that he has running on his KIMSI. I'll try to get more details on this system from CGRS for the next issue).

SYM ON-BOARD SPEAKER TOGGLE ROUTINE

from Bruce McKenzie

This is a subroutine to invert the state of the SYM's on-board speaker. If it is called regularly, it will produce an audible tone. Use it as you would 'INC 1700' on the KIM, or 'INC A000' on the SYM. This routine saves all registers, and is totally relocatable. As it stands now, memory locations 90D and 91C must be modified to point to an unused zero page location to hold the flag.

One final word- the speaker, being electrostatic works best at higher frequencies.

```
0090 XX          Flag location-will be either '06'
                  or '08'
0900 20 88 81    JSR SAVER
0903 D8          CLD
0904 A9 0D       LDA #0D
0906 20 86 8B    JSR ACCESS
0909 20 A5 89    JSR CONFIG
090C A5 90       LDA FLAG
090E C9 06       CMP #06
0910 F0 06       BEQ *+6
0912 A9 06       LDA #06
0914 D0 02       BNE *+2
0916 A9 08       LDA #08
0918 8D 02 A4    STA OUTREG
091B 85 90       STA FLAG
091D 4C C4 81    JMP RESALL
0920
```

Courtesy of the San Fernando Valley 6502 Users Group.

SYM

SYM BASIC CASSETTE NOTES

from Eugene Garapic
14231 Thompson
Brookpark, OH 44142

I've found a bug in SYM BASIC.

The problem is that you can't save or load Basic programs from WARM START. You can see the problem if you leave Basic and then re-enter Basic through the WARM START location (so as not to clear the BASIC program). You'll find it impossible to save the program on tape in the Basic format.

Fortunately, the fix isn't difficult. Simply key in the following machine language program when you want to re-enter Basic. Install this routine in high memory as not to interfere with your Basic program.

```
20 86 8B JSR ACCESS; UNPROTECT SYSTEM RAM
4C 00 00 JMP WARMSTART; AND RE-ENTER BASIC
```

WARM START is at location $0000 and jumps to location $C27E. COLD START is at $C000 and jumps to $DE6D.

As for the SYM cassette interface:

Put a capacitor in series with the SYM audio output for 1000% better results. Why? Because this isolates the D.C. component in SYM's audio output from the recorder input. (a .01 uf works fine).

The cassette recorder must have enough power to drive SYM's LED recording indicator or else you are working in the critical mode and will get unpredictable results. Use a recorder with at least 1 watt output. The SANKYO ST-50 (available locally for about $40.00) cassette recorder has a tape counter, automatic shutoff, and works great with SYM.

AIM info

Some Useful
AIM NOTES

from Al Davidson
5746 Ballenmoor
Memphis TN 38118

Rockwell has come up with the KIM owner's finest fantasy. Easy-on-the-eye display, easy-to-operate cassette interface, easy-to-peck-on-keyboard, easy-to-use printer; It's all there, 6502 fans!

The bare AIM 65 is a prize alone, not to mention basic, which is at last her (got mine 6/20).

This is certainly the machine for the bells and whistles addict, but you want more? Here are a few tried and true suggestions-----

2MHZ OPERATION-Cut the run on top of the board connecting pin 12,Z10 to pin 5,Z10. Connect pin 12 to the common on a spdt switch. Also connect pin 5,Z10 and pin 8,Z10 to the remaining two terminals on the switch. This allows you to select 1 or 2MHZ operation. The printer operates a great deal less than perfect at 2M, and of course, the cassette info will be twice as fast. This may or may not agree with your recorder, but it performs 200% with the superscope mod# C-108. A more elaborate means for switching may incorporate the CS line for Z32, which is used for both printer and cassette. This could slow the clock down to 1MHZ when the cassette or printer are being "spoken" to.

By the way, doubling the proc. speed has no detremental effects on the machine when running basic along with an extra 4K of 2116 memory added on-board piggy-back style. Fast-Basic fans, take note!! (This is however, recommended for on-board systems only.)

more→

2716's- The ROM sockets on-board can easily be used for 2716 (5V) eproms. Cut the run under the socket connecting pin 18 to all, and jumper 18 to gnd. Since the 2716 is only a 2K eprom, it appears twice in memory; at the first and second 2K boundarys of the socket. If you don't mind that, plug 'em in!

KIMSI-The AIM is billed as being hardware compatible with KIM-close! But no cigar! The difference (other than obvious address decoding brought out to the connectors) is in the generation of RAM R/W on pin E-Z. The KIM circuit nands buffered phase 2 with inverted R/W. The AIM nands buffered phase 2 with buffered R/W. El Wrongo! But easy to remedy, if you're surgically inclined. First, disable the sys R/W to pin 4, Z13. Cut the trace at pin 4 and also the trace that runs under the cip and towards Z32. Now, jumper pin 4,Z13 to pin 5,Z16, which is the correct phase of the R/W line. Now, to re-establish R/W to Z32, jumper pin 22,Z32 to pin 6,Z16. This takes care of the RAM R/W difference.



FIG 1. GENERATES NEW K-ENABLE SUITABLE FOR AIM MEMORY MAP. SEE ALSO KIMSI MANUAL PAGE A4 (3) FIGURE 'C'.

Next, to accomodate AIM's memory map, we have to create a new K-enable. This is explained on page A4(2) of the KIMSI manual, but the general idea is to tell the KIMSI to turn itself off when the proc. is "talking" to a device on it's own board. I used the circuit in fig. 1 on a small piece of breadboard mounted on the AIM. This, I thought, was better than running 8 lines to the KIMSI prototype area. As explained in the KIMSI manual. The KIMSI decoding circuitry has to be disabled by cutting the "V" shaped run under the board at Z11, pin 11.

Now, connect the new K-enable line to KIMSI pin 4 and enjoy!

These two mods render a trouble-free machine, as far as AIM-KIMSI interface goes, but the extra circuitry along with the added lead length to the KIMSI prohibits the use of a 2 MHZ clock.

The 9-digit Microsoft Basic-in-ROM is certainly worth the 100 bucks. Room is provided on board for the ROMS. The peek and poke statements make access to ports and memory convenient, & the 'wait' statement provides high-level port-watching that's easy. Access to user machine language routines could have been easier, but at least it's provided for. Cassette save & load commands are certainly worth honorable mention, too.

This is a real 8K basic, with an impressive list of string handling and arithmetic functions not to mention the usefulness of the error codes and good documentation.

Although the basic is well incorporated into the AIM system using the keyboard, printer, and display, user I/O may easily be used instead, as with all the other AIM I/O functions. (I'm using a KENT-MOORE video board in the KIMSI for output).

AIM TAPE PROBLEMS

from Steve Bresson
1666 Independence Ct
Severn, MD 21144

I have found two problems with the AIM65, both in the tape I/O area.

I. The first is in using the LOAD, (L), command to input object code from tape. When the last record of a file occurs within 6 or 7 bytes of the end of a BLOCK, the loader will either hang up while looking for another block of input, or give an ERROR when it finds another block, which does not have the correct block number.

The error is in the LOAD ($E2E6) program. It first reads the record length, and then the ADDRESS/# of Records, depending on the type of record. If the record length in 00, then the record is the last in the file, and it attempts to read (5+1=)6 bytes from the input buffer. But there are only 3 bytes left from the valid input data , so that if there is enough garbage at the end of the buffer, nothing will happen. When the last byte of the record occurs in the last 2 bytes of the buffer, the input routine attempts to read another block to get the additional data. This causes the hang-up/error.

	1	5	1		
BEGIN FILE	BLK#	FILENAME	ØD	RECORD / RECORD	
NORMAL RECORD	";"	#BYTES	STARTING ADDR.	DATA	ØD
LAST RECORD	";"	ØØ	# RECORDS	CHECKSUM	ØD

The error can be easily shown by the following procedure:

1) place known data in $200-220
2) do a DUMP, (D), to tape, (T) and dump the following blocks of data in one file:
   $200-217,
   $200-207,
   $200-209.
3) rewind the tape and check it using the verify, (3), command. This should show no problems
4) rewind again, and attempt to load, (L). When it hangs, do a RESET, and look in the tape buffer ($116-165). Your data should be there along with the record data.

NOTE: While this problem may not occur too often, it can be a pain when it does, if you do not know what is happening.

II. The second problem is an incompatability between the AIM BASIC tape output and that used by the TEXT EDITOR, and expected by the verify, (3) command. The text editor puts out, and expects to receive a text file ended with a double (CR). Basic can read a text editor file as long as a (ctl-Z) is the last character in the file before the (CR) (CR). But, when Basic writes a file, it puts out a (CR) (LF) (CR) (LF) (CTL-Z) at the end. Both the editor and verify hang-up when reading this.

SOME PERSONAL VIEWS ON HOW AIM COMPARES...

by Jim Butterfield
Toronto

AIM vs KIM

1. AIM cost more.
2. The AIM power supply is a bit tougher than KIM's: 24 volts at 0.5 amperes is harder to procure than KIM's 12 volts at about 0.1 amp, even allowing for the fact that the 24 volts doesn't need regulation.
3. AIM's display is larger, but tougher to work, since it's mostly planned for serial ASCII input; you can't get to individual segments as you can with KIM.
4. KIM has a more flexible system for re-arranging memory; AIM is directed more towards a completely fixed memory map.
5. AIM's built-in printer is a great bonus, even if you have to live with 20 columns.
6. The basic AIM system has spendid monitor features, including Single-step and Breakpoint, with options such as register display and next-instruction disassembly.
7. AIM also has a disassembler and mini-assembler in the basic monitor; they are very handy.
8. AIM's plug-in assembler and plug-in Basic chips make these enhancements simple to add. Extra memory (up to 4K) also goes on-board.
9. There are cassette recorder control lines for AIM, although I haven't been able to make mine work. AIM will write KIM-compatible tape; but its own format is quite nice, and the display gives you a running commentary on what's happening during saves and loads.
10. The text editor is a nice built-in feature; not an earth-shaker, but handy enough.
11. KIMs outnumber AIMs by a very large margin. There are more opportunities to find other KIM-users, programs, etc.

AIM vs PET

1. PET costs more.
2. PET's power supply is built in; you have to go hunting for an AIM power supply, and it's extra.
3. The full CRT display of the PET is of course much more useful than AIM's little 20-character LED strip. PET also has graphics and/or lower case. PET's CRT, however, increases weight and size; AIM (when suitably packaged) is far more portable.
4. AIM may be expanded on-board to 4K; depending on the model, PET may have up to 32K of RAM built in.
5. PET does not come with a printer; AIM does. It costs a fair piece of change to add a printer to PET, although such a printer would of course have more than 20 columns. AIM has a built-in teletype interface if needed; PET needs an adapter to do this.
6. AIM's monitor is excellent for machine-language work. PET's machine language monitor is much less powerful. Enhanced monitors are being passed through the PET user community, but even these don't have all the features that are built into AIM.
7. AIM Basic (an optional extra) is very similar to that of PET. Pet's is somewhat better. I particularly miss the SYS command which isn't available on AIM. Basic file handling is somewhat better on the PET.
8. PET can be expanded with disk and printer to a quite powerful standard system. AIM is capable of this, but there are no standard Rockwell products for this kind of expansion, and each user tends to be on his own.
9. PET' outnumber AIMs by a large margin. There are more opportunities to find other PET-users, programs, etc.

65XX chip family stuff

6522 USER NOTES

from John T. O'Donell
Aydin Monitor Systems
401 Commerce Drive
Fort Washington PA 19034

1. Recently attended a marketing presentation by Synertek in Philadelphia. Conrad Boisvert of Synertek introduced their 6500 family UP's and support chips including the 6522. Enclosed you will find a copy of the SY6522 spec document given out at the presentation. Haven't gone thru all of it in detail but it appears to answer a lot of questions and correct a lot of errors found in the MOS Technology document.

2. Conrad says that Synertek has corrected the problem with the shift register shifting in at system clock rate and generating 9 clock pulses per shift operation instead of 8. The corrected devices are supposed to be available now, but, according to Conrad, there is no change to the part number. Thus you have to go by date code (buy the most recent).

3. The uncorrected device can still be used for shifting in at system clock rate since it does stop shifting and generates an interrupt after 8 clock pulsrs. The extra shift clock pulse presents a problem only for the device providing the serial data. If that device readies more than 8 bits at a time in its serial output shift register then there will be a problem. However, if after each serial byte transfer the controlling UP causes the remote device to load its next byte into its serial output register then the extra clock pulse will be ignored. Naturally there is no problem if the remote device is another 6522.

4. Having said all that we come to a subtlety in the timing of the shift-in operation that will cause a problem if the remote device is other than another 6522. The subtlety involves the timing relationship of the data on CB2 to the rising edge of the shift clock on CB1: the data should be held stable for one full 02 clock cycle after the rising edge of CB1 shift pulse. In our application we wanted to load a byte of data into a 74LS299 universal shift register and then shift it into a 6522. So we connected the serial output of the LS299 to CB2 and connected the shift clock from CB1 to the SL299 clock input. We were using shift-in at system clock rate and each byte acquired was shifted left by 1 bit. When I observed that there were 9 shift clocks I thought I had the answer to the problem and called MOS TECHNOLOGY to find out what to do about it.

   I spoke to Rich Gapin there who told me that although there are 9 shift clocks the 6522 interrupts and stops shifting after 8 so that wasn't the cause of the problem. Subsequent discussion revealed the timing constraints and made apparent that there had to be an extra stage of storage between the output of the LS 299 and CB2. Consequently the serial input data goes to the D input of a 74LS74 clocked by the CB1 shift clock. Q output of the LS74 connects to CB2. The LS299 and LS74 both shift data on the rising edge of the clock. Therefore each bit shifted out of the LS299 will be stable at CB2 input immediately after CB1 clock rising edge.

A COUPLE OF 6522 APPLICATIONS NOTES

from Conrad Boisvert
Synertek Inc

SY6522 Generating Long Timed Intervals

The SY6522 Versatile Interface Adapter contains two 16-bit counter/timers for a variety of purposes, among them the generation of timed interrupts. Each counter is 16 bits long, so the maximum count-down is 2^{16} or 65,536 counts. With a 1MHz processor clock rate, this translates to a maximum time of about 65.5 msec.

In some cases, this may not be long enough. To achieve longer timed intervals, several schemes may be used. Among them are:

1. Increment or decrement a memory location each time the timer interrupt occurs. In this way, an additional factor of up to 256x can be achieved, resulting in a maximum of about 16.8 seconds. However, extra program steps are needed.

2. The two SY6522 timers may be connected externally (Figure 1), resulting in an effective 32-bit counter/timer. In this way, intervals longer than one hour may be achieved.



Figure 1-Connection to Use T1 and T2 as 32-bit Counter

PROGRAMMING CONSIDERATIONS

To cascade the two counters together it is necessary to do the following:

1. Connect PB6 and PB7 together. These pins will not be useable as general I/O functions in this case.
2. Program T1 mode to free-run with output on PB7.
3. Program T2 mode to count pulses on PB6 input.

In this way, the waveform on PB7 is,



Since timer T2 pulse-counting mode counts negative-edge transistions, it is clear that T2 will decrement as follows:



Thus, T2 decrements will occur at the following intervals,

T2 RATE=2x (T1 COUNT) x (Ø2 PERIOD)

And, hence, the total time will be,

T = 2x(T1 count) x (T2 count) x (Ø2 period)

Thus, the maximum is 2 X 65,536 x 65,536 x 1 us = 8590 seconds = 142 minutes = about 2½ hours.

SY6522 - GENERATING A 1Hz SQUARE-WAVE SIGNAL

The SY6522 (Versatile Interface Adapter) has two integral 16-bit timers intended to perform a variety of programmable functions. One capability is to use timer T1 to generate a continuous square-wave output on peripheral pin PB7.

The timer is clocked by the system clock, Ø2, which normally operates at 1MHz. The waveform generated is illustrated in Figure 1.



Figure 1 - PB7 output Waveform

Note that the period of the waveform is 2N+4 cycles, with a 16-bit counter, the maximum number of cycles is where N is the number set into the timer.

$$N_{MAX}=2^{16}-1 = 65,535$$

Hence, the maximum programmable period is

$$P_{MAX}=2N_{MAX}+4= 131,074 \text{ cycles.}$$

This is about 131 msec for a 1MHz system clock, considerably less than 1000 msec, the period of a 1Hz signal.

One way to extend the period is to use the PB7 output signal as a clock input to the shift register on the SY6522. If a pattern of 11110000 is set into the shift register, then the output of the shift register will appear as in Figure 2.



Figure 2 - Shift Register Output Waveform

Note that the period is extended by a factor of 8 by this method.

$$P_{MAX}=8\ (2N+4)$$

Hence, for 1 Hz, P_{MAX} = 1,000,000 and N = 62,498. Thus, it is necessary to store the number, 62,498, into the timer T1 in order to generate the 1 Hz waveform. When translated into hexadecimal format, the result is F422, and F4 is loaded into the high byte and 22 into the low. The step-by-step sequence for programming this is shown in Figure 3.

Note the expecially the following points:

* Loading the T1 high-order counter (Register 5) initiates the timer in its free-running mode.
* PB7 data direction must be set to an output for the pulses to occur.

```
0005  2000                ;PROGRAM TO GENERATE 1HZ SQUARE-WAVE OUTPUT
0010  2000                ;ON 6522 PB7 OUTPUT PIN USING T1 TIMER
0015  2000                ;AND SHIFT REGISTER
0020  2000                ;
0025  2000                ;----------SY6522 ADDRESSES----------
0030  2000                DDRB   =$A802          ;DATA DIRECTION REG
0035  2000                T1CH   =$A805          ;T1 HIGH BYTE
0040  2000                T1LL   =$A806          ;T1 LOW BYTE
0045  2000                SR     =$A80A          ;SHIFT REGISTER
0050  2000                ACR    =$A80B          ;AUXILIARY CONTROL REG
0055  2000                ;
0060  2000                       * =$0200        ;START ADDRESS
0065  0200
0070  0200  A9 F0                LDA #%11110000
0075  0202  8D 0A A8             STA SR          ;STORE SHIFT PATTERN
0080  0205  A9 DC                LDA #$DC
0085  0207  8D 0B A8             STA ACR         ;SET UP T1 AND SHIFT REG
0090  020A  A9 22                LDA #$22
0095  020C  8D 06 A8             STA T1LL        ;LOW BYTE
0100  020F  A9 F4                LDA #$F4
0105  0211  8D 05 A8             STA T1CH        ;HIGH BYTE + START
0110  0214  A9 80                LDA #$80
0115  0216  8D 02 A8             STA DDRB        ;SET PB7 AS OUTPUT
0120  0219  4C 19 02    LOOP     JMP LOOP        ;PROGRAM HALT
0125  021C
0130  021C                       .END
```

6551 ACIA MINI-SPECS

SYNERTEK has recently released a very interesting new addition to the 65XX family. It's called the 6551 Asynchronous Communication Interface Adapter (ACIA) and is a considerable upgrade to the present Motorola 6850 ACIA. The best feature of the 6551 is the on-chip baud rate generator. The baud rate is software programmable and generates 15 baud rates (50 to 19.2 K baud) from a standard 1.8432 MHZ external Xtal. There's also an external 16X clock input for non-standard baud rates (up to 125 Kbaud). I just finished wire wrapping up an HDE prototyping card, with two 6551's which are driven by a single 1.8432 MHZ Xtal in a TTL oscillator configuration. (By the way, I'm using the lowest cost battery operated wire-wrap gun from OK Machine & Tool and it's been working like a champ. I whole heartedly recommend wirewrap for getting prototypes up and debugged quickly.)

This board will serve as the system I/O module for use by my homebrew 6512 CPU board in my "dream machine".

One of the 6551's will be used by my Hazeltine CRT while the other will be driving my printer. Both will be RS-232. Later, I may build up another board for modem control.

The 6551 is, of course, fully programmable as far as: word lengths; number of stop bits; parity bit generation and detection; interrupt operation etc. Also, modem control signals are provided. A very versatile chip indeed!

Get more info from SYNERTEK or ROCKWELL.

Eric

BUGS

ouch!!!

THE CASE OF THE SWITCHED SOFTWARE

Bruce Nazarian

Sharp-eyed readers of 6502 Notes will already have noticed my inadvertent error in issue #15, re: music mods.

Author Armand Camus is, in fact, quite correct in his references to the page zero locations used in his software. Not having the original software (as published in BYTE) handy, I had no way to know his references weren't incorrect: so, be aware, you KIM music lovers-the BYTE (also COMPUTERIST) software is not the same as the Advanced Music Software being marketed by MTU.

Also, in recent conversations with Dave Cox, Marketing manager for MTU, I was advised of the existence of a NEW KIM DAC board, which Dave assures me will outperform the old DAC..It must be quite a board, as the old DAC was nothing to sneeze at! Several changes have been made, but all for the better. The new board only requires a single supply voltage (+5), and should have an improved signal-to-noise ratio over the old one. I have ordered a new one from them and will have a user's report as soon as I have it up and running.

My sincere apologies to any readers I may have caught off-guard with my software mistake, and sincere apologies to author Camus for doubting his eyesight!!!

BUGS IN #15, PAGE 4

There are some errors in the wiring sketch (fig. 4) for the dynamic RAM board. The schematic on the pre ious page is believed correct however. The problem in the wiring sketch involves placement of the address lines so the sketch is still useable once the address lines are referenced to the correct pins on the RAM chips.

BUGS IN #15 PAGE 22,23

The article by Cass Lewart, 1:32640 should be 1:32896 the ocrrect formula is:

$$(FF\ hex + 2) \quad \frac{(FF\ hex + 1)}{2} \quad K = 0$$

and the last row of numbers in the table should be: 32.9 ms, 263 ms, 2.11 ms, 33.7 sec.

PAGE 26

Reverse the polarity of the diode placed across the 5 volt relay.

OSI

READ KIM TAPES ON YOUR OSI SYSTEM

By Robert Solomon
5868 Joanne Ct.
North Ridgeville OH 44039

In my previous letter, I stated that I was developing a high speed PLL tape interface for the OSI. After looking at the benefits of that approach, I have abandoned that idea. It would be of much greater help to the OSI experimenter to increase his access to cassette-based experimenter software.

A greater amount of 6502 experimenter software is available to the KIM owner than will probably ever be available to the OSI owner. So all that needs to be done is to make the OSI system compatable with the KIM tape format. I have an OSI 404V CPU and the owners manual says you can install a KIM chip on the board. It is not quite that easy, as I found out when I studied the operaiton of the KIM 6530 chip. The solution to that problem is explained in this article.

As I described in my previous letter, I have a 16K system consisting of two 4K boards and one 8K board. I also stated I was in the process of implementing KIM Focal 65. Focal for KIM resides at 2000 to 360A with user program above 360A. If my 16K of memory were continuous from 0000, I would only have about 2¼K of user workspace. But I need to have the memory continuous for my Tiny Basic which starts at 0200. So I set up my memory as follows:

4K from 0000 to 0FFF for page zero and I/O to teletype, CRT, and KC format tape;

8K from 2000 to 3FFF for general use (including Focal); and 4K which can be placed at either 1000 ro 1FFF ro 4000 to 4FFF controlled by a front panel DPDT switch.

Now I can run either Tiny or Focal and have workspace located as needed based on the front panel switch position. I also plan on using 9-digit Microsoft KIM Basic located from 2000 up.

All I need is a method to load KIM tapes into the OSI. There is also a high speed tape format for KIM called hypertape; and Lou Edwards has available a 4800 baud Zip-tape system for KIM. It would be nice to be able to use these on the OSI.

Implementing the 6530 chip was not quite as simple as one would expect. In order to understand the problems, you need to understand the KIM program. (Anyone contemplating using the KIM simulator should get a copy of the KIM-1 Users Manual.)

Each 6530 includes 1K of ROM, 64 bytes of RAM, i/o ports, and a timer. The 6530-002 chip ROM contains the KIM keyboard, display, and TTY operating programs. The 6530-003 chip ROM contains the tape interface program. The problem is that the -003 ROM program uses the RAM, I/O, and timer on the -002 chip! The tape programs also exit to a location in the -002 ROM.



KIM-1 TAPE INTERFACE

The solution to this problem is shown in the second schematic. I managed to fit it all on the CPU board, but I recommend putting it on a separate board. Then you could install the tpae interface circuit on the board also. (A prototype board is available from D&N Micro Products, 3932 Oakhurst Dr., Fort Wayne, IN, 46815, for $27.00 including postage, handling, and connectors.) My solution involved circuitry to make the 6530-003 use its own RAM, I/O, and Timer for the tape functions. I also implemented a 1K RAM at 1C00 to 1FFF and the tape program will exit into this RAM.

The 7404, 7420, and 74145 decode the six high order address lines to provide the selects for the 6530 I/O, Timer, and RAM. (K5 to CS1 for 1400-17FF); 6530 ROM (K6 to RS0 for 1800-1BFF); and the 1K RAM (K7 to 2102 CE for 1C00-1FFF) Address lines A0 thru A9 go directly to the 6530 except for A6. The proper handling of A6 is really the solution to the whole problem.

The selection between the 6530-002 and the 6530-003 is made by RS0 and A6. When RS0 is low, A0 thru A9 must directly access the 6530. RS0 for the 003 is connected to K6 and the RS0 for the 002 is normally connected to K7. I use K7 to select the 1K RAM instead of the 002 chip. When RS0 is high, the 6530 is selected by CS1 being low. Both the 002 and 003 respond to K5 connected to CS1. The 002 and 003 are distinguished by the status of A6. A high on A6 selects the 002 and a low on A6 selects the 003.

So all we have to do is invert A6 to select the 003 I/O, RAM, and Timer for the tape interface. I used the 7486 Exclusive-OR gate to perform this function. When K6 is low (ROM Select) A6 is not inverted and we have access to the tape program in ROM. When K6 is high (at all other times) A6 is inverted and we have access to the 6530-003 RAM, I/O, and Timer to support the KIM tape interface.

The 1K RAM is necessary because the tape ROM program exits to an address in the 6530-002 ROM program. Unless we have something at that destinaiton, the machine could run wild and do who knows what to the program. An advantage of having this 1K RAM is that you can run KIM programs as is, with appropriate vectors or subroutines in the 1K RAM. This will make it unnecessary to make patches within the main program in many cases.

You will notice that there is a disable switch in the 6530 circuit. Since my system has that movable 4K block of memory, I cannot have the 6530 or 1K RAM functional when the block is located at 1000-1FFF. I have done this by disabling the 7420 decoder IC and by forcing the R/W low to both the OR-wired 7403 on the 1K RAM and the 6530. This prevents both systems from putting data onto the data bus when they are disabled.

Now that we have the hardware, we need the software to make it work. At this point, I will leave this up to the reader. In the future, I plan to submit software information. (Boy! what a sneaky way to make you subscribe to User Notes). Besides, I have to leave room in this issue for other stuff.



RSØ	A6	IC-3 OUT
0	0	0
0	1	1
1	0	1
1	1	0

145 DECODER						
D	C	B	A	K5	K6	K7
0	1	0	1	0	1	1
0	1	1	0	1	0	1
0	1	1	1	1	1	0
1	X	X	X	1	1	1

$\overline{K5}$ for 1400-17FF - 6530 I/O, TIMER, RAM
$\overline{K6}$ for 1800-1BFF - 6530 ROM
$\overline{K7}$ for 1C00-1FFF - 1K RAM

	IC	MEM	6530
A9	K-8	14	5
A8	K-2	15	6
A7	K-4	16	7
A5	B-6	2	10
A4	B-4	7	11
A3	B-2	6	12
A2	B-8	5	13
A1	B-10	4	14
AØ	B-12	8	15

WHAT IS KIMATH?

Some of you have asked for more details on the KIMATH program that we are making available.

KIMATH is a group of floating-point math subroutines capable of performing operations up to 16 decimal digits of precision. The functions supported by KIMATH include ADD, SUBTRACT, MULTIPLY, DIVIDE, LOG, ANTILOG, TANGENT, ARTANGENT, and SQUARE ROOT: Special subroutines are included to evaluate polynomial expressions, which can be used to approximate most math functions.

It should be stressed that KIMATH is not a complete math package, only a group of subroutines. (I/O routines are left up to the user). This means KIMATH is totally independent of any operating system dependencies and makes this package useful for most any 6502 based machines, (such as SYM & AIM) not just KIM.

Basically, you would load one or two special register areas (each register can be up to about 20 bytes in length) with the number (s) to be worked on and then call the proper subroutines in KIMATH to do the operation. KIMATH only operates on numbers in an unpacked BCD format, but routines are provided to convert to and from other data formats such as packed BCD, and unpacked ASCII for easier storage and output data formatting. (That's right, KIMATH does its calculating in BCD, not binary).

A useful addition to KIMATH, called MATHPAC, was published in Doctor Dobbs Journal! (volume 2 Issue #10). MATHPAC provides the needed I/O routines and a host of other features, such as variable storage and extended computational ranges not possible with KIMATH alone. MATHPAC needs 2K of additional memory.

Additional info on KIMATH should be gotten from the KIMATH manual - available for around $15.00 from several sources including:

Johnson Computer
P.O. Box 523
Medina Oh 44256
216-725-4560

A B Computers
Box 104
Perkasie Pa 18944
215-257-8195

Falk-Baker
382 Franklin Avenue
Nutley NJ 07110
201-661-2430

The KIMATH manual contains a complete source listing of KIMATH.

KIMATH ON CASSETTE OR EPROM FOR AIM, SYM & KIM & APPLE

KIMATH is now available assembled to any location, and comes with a sorted symbol table for easy routine lookup.

ON KIM COMPATIBLE CASSETTE FOR AIM,SYM,KIM $20.00

ON 2Kx8 5v. EPROM (TI 2516 or INTEL 2716) $80.00
(APPLE VERSION IS ONLY AVAILABLE ON EPROM)

ORDERING INFORMATION:

You must include the following information with your order for cassette and EPROM versions of KIMATH:

Hex starting address for main program (normally $F800)
Hex starting address for 23 bytes of zero-page storage (normally $0000)
Hex starting address for 154 bytes of RAM for the argument registers (normally $0200)

ORDER FROM:

6502 USER NOTES, POB 33093, N. Royalton, Ohio 44133

REVIEWS ETC.

PRODUCT REVIEW by the Editor

THE MORE BOARD FROM T.T.I.*

Frankly, I wasn't exactly overjoyed when I received this product for review. After all, why should 3K of RAM expansion turn me on when I had over 10 times that much on my regular system.

My big change in attitude concerning the MORE board came after I realized that my other EPROM burner just would not program the Texas Instruments 2716 because of incompatabilities.

I even started to design an EPROM burner that would program the TI2716 when I suddenly realized that the solution to the problem was already at hand.

Upon a closer look at the MORE board, I discovered a very nicely engineered EPROM programming system which works with all of the popular EPROMS (2708, INTEL 2716, TI 2716, and 2516) eliminates the need for any voltages besides the usual KIM +5 and +12, and includes enough RAM on-board to solve the problem of how to burn a 2K EPROM when you have only 512 bytes of useable RAM.

The MORE board has turned my spare KIM into an EPROM programming system which has twice the capability of some of the commercial EPROM programming units at a fraction of the cost.

I haven't gotten around to burning the TI2716 yet, but I have put my disk system bootstrap into a 2708. The board performed flawlessly. Since MORE has two on-board EPROM sockets (one for programming and the other mapped into normal memory space), EPROMS can easily be copied. Of course, the EPROM burning software (which is included with the MORE in the form of complete source listings) can be relocated and burned into a 2708 for semi-permanent storage in the memory-mapped EPROM socket if you really don't need this copying capability.

The only negative things I can say about the MORE board are that I had to do a little trimming on the connector to get it hooked up to KIM and the preliminary documentation has a few soft spots.

A small file took care of the first problem and the second problem, according to T.T.I., is in the process of being corrected.

I forgot to mention that the board appears to be of industrial quality with all IC's socketed and two quick load zero insertion Textool sockets for the EPROMS. No EPROMS or RAMS are included. MORE comes fully assembled and, according to T.T.I. can also be used on the Rockwell AIM system.

I'm happy with the MORE board, plan on using more EPROMS in the near future and will probably cause a real scene when T.T.I. asks for their board back!

MORE is available for $170 from T.T.I., POB 2328, Cookeville, Tn 38501.

PRODUCT ANNOUNCEMENT

FLOPPY DISK FOR THE AIM-65

COMPAS Microsystems (224 S.E. 16th St, Ames, Iowa 50010) announces availability of a mini-floppy interface for the AIM-65.

"The base price of $850 includes DAIM controller board with all operating system in EPROM, power supply and one packaged disk drive. Price for an additional drive is $350. The components of the DAIM system may also be purchased on an individual basis if the user desires. Delivery is stock to sixty days. The system is currently in production. A complete operating manual will be supplied for evaluation purposes for the nominal charge of $5."

6502 FORTH

* 6502 FORTH IS A COMPLETE PROGRAMMING SYSTEM WHICH CONTAINS AN INTERPRETER/COMPILER AS WELL AS AN ASSEMBLER AND EDITOR.
* 6502 FORTH RUNS ON A KIM-1 WITH A SERIAL TERMINAL. (TERMINAL SHOULD BE AT LEAST 64 CHR. WIDE)
* ALL TERMINAL I/O IS FUNNELLED THROUGH A JUMP TABLE NEAR THE BEGINNING OF THE SOFTWARE AND CAN EASILY BE CHANGED TO JUMP TO USER WRITTEN I/O DRIVERS.
* 6502 FORTH USES CASSETTE FOR THE SYSTEM MASS STORAGE DEVICE
* CASSETTE READ/WRITE ROUTINES ARE BUILT IN (INCLUDES HYPER-TAPE).
* 92 OP-WORDS ARE BUILT INTO THE STANDARD VOCABULARY.
* EXCELLENT MACHINE LANGUAGE INTERFACE.
* 6502 FORTH IS USER EXTENSIBLE.
* 6502 FORTH IS A TRUE IMPLEMENTATION OF FORTH ACCORDING TO THE CRITERIA SET DOWN BY THE FORTH INTEREST GROUP.
* SPECIALIZED VOCABULARIES CAN BE DEVELOPED FOR SPECIFIC APPLICATIONS.
* 6502 FORTH RESIDES IN 8K OF RAM STARTING AT $2000 AND CAN OPERATE WITH AS LITTLE AS 4K OF ADDITIONAL CONTIGUOUS RAM.

6502 FORTH PRICE LIST

KIM CASSETTE, USER MANUAL, AND COMPLETE ANNOTATED SOURCE LISTING ($2000 VERSION) $90.00
PLUS S&H 4.00

OUR USER MANUAL ASSUMES SOME PREVIOUS KNOWLEDGE OF FORTH.
IF YOU HAVE NO IDEA WHAT FORTH IS ALL ABOUT— SEND AN S.A.S.E (BUSINESS SIZE) AND ASK FOR A "FORTH BIBLIOGRAPHY"

USER MANUAL (CREDITABLE TOWARDS SOFTWARE PURCHASE) $15.00
PLUS S&H 1.50

AIM & SYM VERSIONS TO BE AVAILABLE

6502 USER NOTES
POB 33093
N. ROYALTON, OHIO
44133

also for the HDE floppy

KIM SOFTWARE ON CASSETTE

FOCAL CASSETTE OPERATING SYSTEM ($4000-$4920) includes instructions, cassette and complete source listing. Price includes shipping & handling (see FOCAL section in this issue for more info)(works with either verison of FOCAL).	$37.50
BASEBALL (from this issue)	6.00
BASEBALL source listing (16 pages)	5.00
KIMATH (specify $2000 or $F800 version) (includes manual erata sheet)	12.00
HEXPAWN (from issue #13)	5.00
DISASSEMBLER (from issue #14)	5.00
BANNER (from issue #14)	5.00

These cassettes are original dumps, not copies, made with top quality 5-screw housing cassettes in the HYPERTAPE X 3 tape speed. Thirty seconds of sync characters precede the program to enable you to tune up your recorder or PLL.

Payment must be in U.S. Funds. Overseas customers please include $1.00 extra per cassette for extra postage.

6502 USER NOTES, POB 33093, N. Royalton 44133

HDE inc.

BOX 120
ALLAMUCHY, N.J. 07820
201-362-6574

HUDSON DIGITAL ELECTRONICS INC.

THE HDE MINI-DISK SYSTEM



VERSIONS

KIM

TIM

AIM 65 – 4th Qtr. '79

SYM – 1st Qtr. '80

SINGLE DRIVE	**$ 795.00**
DUAL DRIVE	**$1195.00**

Complete with all hardware. Interconnecting cables, FODS, text editor and user and installation manuals.

The HDE DM816-MD1 Mini Disk System is the peripheral you have been waiting for. No longer bounded by long and unreliable cassette saves and loads, your computer becomes a sophisticated system for program development or general purpose use. With the HDE Mini-Disk you load and save programs in seconds, not minutes or hours. And, since all transfers to and from the Mini-Disk are verified for accuracy, the data will be there when you need it.

The HDE DM816-MD1 Mini-Disk has been "systems" engineered to provide a complete and integrated capability. Software and hardware have been built as a team using the most reliable components available. The systems software includes the acclaimed and proven HDE File Oriented Disk System and Text EDitor, requiring only 8K for the operating software and overlay area. Systems expanding programs available include the two-pass HDE assembler, the Text Output Processing System and Dynamic Debugging Tool. Hardware includes a Western Digital 1771 based controller in a state-of-the-art 4½ x 6½" card size, Shugart SA 400 drive and the Alpha power supply.

The storage media for the DM816-MD1 is the standard, soft sectored 5¼" mini diskette readily available at most computer stores, and HDE has designed the system so that the diskettes rotate only during disk transactions, favorably extending media life. A disk formatter routine included with the system, formats the diskettes, verifies media integrity by a comprehensive R/W test and checks drive RPM. Additional utilities provide ascending or descending alpha numeric sort, disk packing, text output formatting, file renaming, file addressing and other capabilities.

HDE PRODUCTS. BUILT TO BE USED WITH CONFIDENCE.

AVAILABLE DIRECT OR FROM THESE FINE DEALERS:

JOHNSON COMPUTER	PLAINSMAN MICROSYSTEMS	ARESCO	LONG ISLAND COMPUTER GENERAL STORE	LONE STAR ELECTRONICS
Box 523	Box 1712	P.O. Box 43	103 Atlantic Avenue	Box 488
Medina, Ohio 44256	Auburn, Ala. 36830	Audubon, Pa. 19407	Lynbrook, N.Y. 11563	Manchaca, Texas 78652
216-725-4560	800-633-8724	215-631-9052	516-887-1500	612-282-3570